arXiv:1202.1332v1 [cs.IT] 7 Feb 2012

Secure Multiplex Coding with Dependent and Non-Uniform Multiple Messages

Masahito Hayashi , Ryutaroh Matsumoto

***Abstract*—The secure multiplex coding (SMC) is a technique to remove rate loss in the coding for wiretap channels and broadcast channels with confidential messages caused by the inclusion of random bits into transmitted signals. SMC replaces the random bits by other meaningful secret messages, and a collection of secret messages serves as the random bits to hide the rest of messages. In the previous researches, multiple secret messages were assumed to have independent and uniform distributions, which is difficult to be ensured in practice. We remove this restrictive assumption by a generalization of the channel resolvability technique.**

We also give practical construction techniques for SMC by using an arbitrary given error-correcting code as an ingredient, and channel-universal coding of SMC. By using the same principle as the channel-universal SMC, we give coding for the broadcast channel with confidential messages universal to both channel and source distributions.

***Index Terms*—broadcast channel with confidential messages, information theoretic security, multiuser information theory**

I. Introduction

This paper studies a generalization of the channel resolvability problem [8], universal coding for the broadcast channel with confidential messages [5], and the secure multiplex coding [15]. Therefore, we divide the introductory section to three subsections.

A. Generalization of the Channel Resolvability

For a given channel W with input alphabet $\mathcal{X}$ and output alphabet $\mathcal{Y}$, and given information source X on $\mathcal{X}$, Han and Verdú [8] considered to find a coding $f : \mathcal{D} \to \mathcal{X}$ and a random variable D such that the distributions of $W(f(D))$ is close to $W(X)$ with respect to the variational distance or the normalized divergence, and evaluated the minimum resolution of D to make the variational distance or the normalized divergence asymptotically zero. In their problem formulation, the randomness D used to simulate the channel output distribution can be chosen.

In this paper, we shall consider the situation in which we are given a channel W, an information source X, and randomness D and asked to find coding $f : \mathcal{D} \to \mathcal{X}$ such that $W(f(D))$ is as close as possible to $W(X)$ with respect to unnormalized divergence. We shall study how close $W(f(D))$ can be to $W(X)$ in Theorems 10 and 12 in Section IV.

It has been observed that the channel resolvability coding can be used to construct wiretap channel coding [2], [4], [10]. By using our generalized channel resolvability coding in Theorems 10 and 12, one can construct coding for a wiretap channel that can ensure the secrecy of message against the eavesdropper Eve when the randomness used by the encoder is non-uniform and statistically dependent on the secret message that has to be kept secret from Eve. However, one can realize much more than the above, as introduced in the next subsection.

B. Secure Multiplex Coding

In the problem of wiretap coding, there are the legitimate sender called Alice, the legitimate receiver called Bob, and the eavesdropper Eve. There is also a noisy broadcast channel from Alice to Bob and Eve. Alice wants to send secret messages reliably to Bob and secretly from Eve. This problem was first formulated by Wyner [21]. Csiszár and Körner generalized Wyner's original problem to include a common message from Alice to both Bob and Eve, and determined the optimal rate tuples of information rates of the secret message and the common message, and the equivocation rate of the secret message to Eve, which is measured by the conditional entropy of the secret message given Eve's received signal [5]. They called their generalized problem as the broadcast channel with confidential messages, hereafter abbreviated as BCC.

The secrecy of messages over the wiretap channel and the BCC is realized by including meaningless randomness into Alice's transmitted signal. This decreases the information rate. In order to get rid of this information loss, Yamamoto et al. [15] proposed the secure multiplex coding, hereafter abbreviated as SMC, as a generalization of the wiretap channel coding. In SMC, Alice has T distinct secret messages $S_1, \ldots, S_T$. The $T-1$ secret messages $S_1, \ldots, S_{i-1}, S_{i+1}, \ldots, S_T$ serve as meaningless randomness to hide S_i, for each $i = 1, \ldots, T$, and Eve can know little about S_i, for $i = 1, \ldots, T$. Yamamoto et al. did not evaluated the information leakage of multiple messages $S_{i_1}, \ldots, S_{i_n}$ to Eve, and the authors analyzed such information leakage in [19]. The authors also generalized coding in [15] so that Alice's encoder can support the common message S_0 to both Bob and Eve.

There was a restrictive assumption in both [19], [15]. The multiple secret messages $S_1, \ldots, S_T$ were assumed to have statistically independent and uniform distribution. Such assumption is difficult to be ensured in practice, and the assumption was always questioned at the author's presentation in international conferences. The main contribution of this paper is to remove that assumption by using the generalized channel resolvability coding given in Theorems 10 and 12.

M. Hayashi is with Graduate School of Information Sciences, Tohoku University, Aoba-ku, Sendai, 980-8579, Japan, and Centre for Quantum Technologies, National University of Singapore, 3 Science Drive 2, Singapore 117542. (e-mail: hayashi@math.is.tohoku.ac.jp)

R. Matsumoto is with Department of Communications and Integrated Systems, Tokyo Institute of Technology, 152-8550 Japan

Specifically, we shall give two code constructions for SMC. The first one in Section V-B is based on the channel resolvability coding in Theorem 12, while the second one is based on Theorem 10 in Section V-C. The second construction is insufficient to prove the capacity region, but can provide a better exponential decreasing rate of the mutual information of secret messages to Eve under certain situations. By using these constructions, we shall evaluate the decoding error probability and the mutual information to Eve in Section V in the non-asymptotic setting. In Section VI we formulate the capacity region of SMC, analyze the asymptotic performance of two constructions, and prove that the first construction achieves the capacity region of SMC. In Section VII, we shall prove that the mutual information to Eve converges to zero when the normalized mutual information to Eve converges to zero. This property is what is called the strong security [20].

In Theorem 16 of Section V, we show that we can have an upper bound of mutual information between multiple secret messages and Eve's received signal, by attaching random group homomorphisms satisfying Condition 11 to *any* error-correcting code for channels with single sender and single receiver or the broadcast channel with degraded message sets [16]. However, the upper bound in Theorem 16 becomes difficult to be computed when the error-correcting code is not given by the standard random coding in information theory. In Section VIII, we shall give two upper bounds on the mutual information that can be computed easily in practice when the construction of Section V is combined with an arbitrary given error-correcting code. Section VIII is enhancement of our earlier proceeding paper [12].

Universal coding is construction of encoder and decoder that do not use the statistical knowledge on the underlying information system (usually channel and/or source) [3]. In Section IX we shall give a construction of SMC universal to channel. The basic idea in Section IX is to combine the construction in Section V with the universal coding for the broadcast channel with degraded messages sets in [17], while in Sections V–VII the random coding in [16] is used as their error-correcting mechanism. Section IX is enhancement of our earlier proceeding paper [13].

C. Universal Coding for the Broadcast Channel with Confidential Messages

Channel-universal coding for BCC had not been studied before [13], and coding for BCC can be regarded as a special case of SMC. In Section IX and [13] we consider SMC universal to channel, but its universality to the source, that is, the probability distributions of multiple secret messages, is not considered. In Section X we give a coding for BCC universal to both channel and source. Its channel-universality is realized by the same principle as Section IX and [13]. Section X is also enhancement of our earlier proceeding paper [13] toward another direction different from Section IX.

II. BROADCAST CHANNELS WITH CONFIDENTIAL MESSAGES

Let Alice, Bob, and Eve be as defined in Section I. $\mathcal{X}$ denotes the channel input alphabet and $\mathcal{Y}$ (resp. $\mathcal{Z}$) denotes the channel output alphabet to Bob (resp. Eve). We assume that $\mathcal{X}$, $\mathcal{Y}$, and $\mathcal{Z}$ are finite unless otherwise stated. We denote the conditional probability of the channel to Bob (resp. Eve) by $P_{Y|X}$ (resp. $P_{Z|X}$). The task of broadcast channels with confidential messages is the following. (1) Alice sends the common message E to Bob and Eve. (2) Alice confidentially sends the secret message S to Bob. Here, we denote the sets of the common messages and the secret messages by $\mathcal{E}$ and $\mathcal{S}$. Our protocol is given by Alice's stochastic encoder φ_a from $\mathcal{S}\times\mathcal{E}$ to $\mathcal{X}$, Bob's deterministic decoder $\varphi_b : \mathcal{Y} \to \mathcal{S}\times\mathcal{E}$ and Eve's deterministic decoder $\varphi_e : \mathcal{Z} \to \mathcal{E}$. The triple $\varphi = (\varphi_a, \varphi_b, \varphi_e)$ is called a code for broadcast channels with confidential messages. Then, the performance is evaluated by the following quantities. (1) The sizes of the sets of the common messages and the secret messages, i.e, $|\mathcal{E}|$ and $|\mathcal{S}|$. (2) Bob's decoding error probability $P_b[P_{Y|X}, \varphi] := \Pr\{(S, E) \neq \varphi_b(Y)\}[P_{Y|X}, \varphi]$. (3) Eve's decoding error probability $P_e[P_{Y|X}, \varphi] := \Pr\{E \neq \varphi_e(Z)\}[P_{Z|X}, \varphi]$. (4) Eve's uncertainty $H(S|Z)[P_{Z|X}, \varphi_a]$. Since these quantities are functions of the channel and the code, such a dependence is denoted by the symbol $[P_{Y|X}, \varphi]$ in the above notation. Instead of $H(S|Z)[P_{Z|X}, \varphi_a]$, we sometimes treat (5) leaked information $I(S : Z)[P_{Z|X}, \varphi_a]$.

In fact, we sometimes need to evaluate the error probability when S and/or E is fixed. In such a case, we denote it by $P_b(S = s)[P_{Y|X}, \varphi]$, $P_b(S = s, E = e)[P_{Y|X}, \varphi]$, and $P_e(E = e)[P_{Y|X}, \varphi]$.

First, we review the formulation when both of the common messages and the secret messages are subject to uniform distributions. The set $\mathcal{S}_n$ denotes that of the confidential message and $\mathcal{E}_n$ does that of the common message when the block coding of length n is used. We shall define the achievability of a rate triple (R_1, R_e, R_0). For the notational convenience, we fix the base of logarithm, including one used in entropy and mutual information, to the base of natural logarithm.

Definition 1: The rate triple (R_1, R_e, R_0) is said to be *achievable* for the equivocation criterion if the following condition holds. The size of the sets of the common and confidential messages are $|\mathcal{E}_n| = e^{nR_0}$ and $|\mathcal{S}_n| = e^{nR_1}$. The common and confidential messages are subject to the uniform distributions on $\mathcal{S}_n$ and $\mathcal{E}_n$, respectively. There exists a sequence of the code $\varphi_n(\varphi_{a,n}, \varphi_{b,n}, \varphi_{e,n})$, i.e., Alice's stochastic encoder $\varphi_{a,n}$ from $\mathcal{S}_n\times\mathcal{E}_n$ to $\mathcal{X}^n$, Bob's deterministic decoder $\varphi_{b,n} : \mathcal{Y}^n \to \mathcal{S}_n\times\mathcal{E}_n$ and Eve's deterministic decoder $\varphi_{e,n} : \mathcal{Z}^n \to \mathcal{E}_n$ such that

$$\lim_{n\to\infty} P_b[P^n_{Y|X}, \varphi_n] = 0$$

$$\lim_{n\to\infty} P_e[P^n_{Z|X}, \varphi_n] = 0$$

$$\liminf_{n\to\infty} \frac{H(S_n|Z^n)[P^n_{Y|X}, \varphi_{a,n}]}{n} \geq R_e.$$

The capacity region with the equivocation criterion of the BCC is the closure of the achievable rate triples for the equivocation criterion.

Theorem 2: [5] The capacity region with the equivocation criterion of the BCC is given by the set of R_0, R_1 and R_e such that there exists a Markov chain $U \to V \to X \to YZ$ and

$$\begin{aligned} R_1 + R_0 &\leq I(V;Y|U) + \min[I(U;Y), I(U;Z)], \\ R_0 &\leq \min[I(U;Y), I(U;Z)], \\ R_e &\leq I(V;Y|U) - I(V;Z|U), \\ R_e &\leq R_1. \end{aligned}$$

As described in [18], U can be regarded as the common message, V the combination of the common and the confidential messages, and X the transmitted signal.

Here, we propose another type of capacity region.

Definition 3: The rate triple $(R_1,\ R_l,\ R_0)$ is said to be *achievable* for the leaked information criterion if the following condition holds. The size of the sets of the common and confidential messages are $|\mathcal{E}_n| = e^{nR_0}$ and $|\mathcal{S}_n| = e^{nR_1}$. the common and confidential messages are subject to the uniform distributions on $\mathcal{S}_n$ and $\mathcal{E}_n$, respectively. There exists a sequence of the code $\varphi_n(\varphi_{a,n}, \varphi_{b,n}, \varphi_{e,n})$, i.e., Alice's stochastic encoder $\varphi_{a,n}$ from $\mathcal{S}_n \times \mathcal{E}_n$ to $\mathcal{X}^n$, Bob's deterministic decoder $\varphi_{b,n} : \mathcal{Y}^n \to \mathcal{S}_n \times \mathcal{E}_n$ and Eve's deterministic decoder $\varphi_{e,n} : \mathcal{Z}^n \to \mathcal{E}_n$ such that

$$\begin{aligned} \lim_{n\to\infty} P_b[P^n_{Y|X}, \varphi_n] &= 0 \\ \lim_{n\to\infty} P_e[P^n_{Z|X}, \varphi_n] &= 0 \\ \limsup_{n\to\infty} \frac{I(S_n : Z^n)[P^n_{Y|X}, \varphi_{a,n}]}{n} &\leq R_l. \end{aligned}$$

The capacity region with the leaked information criterion of the BCC is the closure of the achievable rate triples for the leaked information criterion.

The capacity region with the leaked information criterion of the BCC is characterized as a corollary of Theorem 2.

Corollary 4: The capacity region with the leaked information criterion of the BCC is given by the set of R_0, R_1 and R_l such that there exists a Markov chain $U \to V \to X \to YZ$ and

$$\begin{aligned} R_1 + R_0 &\leq I(V;Y|U) + \min[I(U;Y), I(U;Z)], \\ R_0 &\leq \min[I(U;Y), I(U;Z)], \\ R_l &\geq [R_1 - I(V;Y|U) + I(V;Z|U)]_+. \end{aligned}$$

That is, when $R_1 + R_0 < I(V;Y|U) + \min[I(U;Y), I(U;Z)]$ and $R_0 < \min[I(U;Y), I(U;Z)]$, there exists a sequence of the code $\varphi_n(\varphi_{a,n}, \varphi_{b,n}, \varphi_{e,n})$, i.e., Alice's stochastic encoder $\varphi_{a,n}$ from $\mathcal{S}_n \times \mathcal{E}_n$ to $\mathcal{X}^n$, Bob's deterministic decoder $\varphi_{b,n} : \mathcal{Y}^n \to \mathcal{S}_n \times \mathcal{E}_n$ and Eve's deterministic decoder $\varphi_{e,n} : \mathcal{Z}^n \to \mathcal{E}_n$ such that

$$\begin{aligned} \lim_{n\to\infty} P_b[P^n_{Y|X}, \varphi_n] &= 0 \\ \lim_{n\to\infty} P_e[P^n_{Z|X}, \varphi_n] &= 0 \\ \limsup_{n\to\infty} \frac{I(S_n : Z^n)[P^n_{Y|X}, \varphi_{a,n}]}{n} &\leq [R_1 - I(V;Y|U) + I(V;Z|U)]_+. \end{aligned}$$

Next, we consider the BCC when the common and confidential messages do not obey the uniform distributions on $\mathcal{S}_n$ and $\mathcal{E}_n$, respectively, i.e., the confidential message S might have a correlation with the common messages E. when the confidential message S is independent of the common messages E,

$$\begin{aligned} & I(S:Z)[P_{Y|X}, \varphi_a] \leq I(S:ZE)[P_{Y|X}, \varphi_a] \\ =& I(S:Z|E)[P_{Y|X}, \varphi_a] + I(S:E)[P_{Y|X}, \varphi_a] \\ =& I(S:Z|E)[P_{Y|X}, \varphi_a], \\ & I(S:Z)[P_{Y|X}, \varphi_a] \\ =& H(S) - H(S|Z) \geq H(S|E) - H(S|Z) \\ =& H(S|E) - (H(S|ZE) + I(S:E|Z)) \\ =& I(S:Z|E) - I(S:E|Z) \\ \geq& I(S:Z|E) - H(E|Z) \\ \geq& I(S:Z|E) - H(E|\varphi_e(Z)). \end{aligned}$$

When the error probability goes to zero exponentially, Fano inequality guarantees that $H(E|Z)$ goes to zero. Hence, $I(S:Z)$ and $I(S:Z|E)$ have the same asymptotic behavior. So, even if we replace $I(S:Z)$ by $I(S:Z|E)$ in Definition 3, we obtain the same capacity region. However, when the confidential message S is not independent of the common messages E, $I(S:Z)$ and $I(S:Z|E)$ have the different asymptotic behavior. Since

$$\begin{aligned} & I(S:Z) = I(S:ZE) - I(S:E|Z) && (1) \\ \geq& I(S:E) - H(E|Z) && (2) \\ \geq& I(S:E) - H(E|\varphi_e(Z)), && (3) \end{aligned}$$

$I(S:Z)$ is lowerly bounded by $I(S:E)$ when the error probability goes to zero exponentially. That is, when the mutual information $I(S:E)$ is finite, it is impossible that the mutual information $I(S:Z)$ goes to zero because Eve can infer the secret message from the common message. Thus, it is not suitable to treat the mutual information $I(S:Z)$ as leaked information. Hence, we adopt the conditional mutual information $I(S:Z|E)$ as leaked information.

Now, we propose the concept of "source-channel universal code for BCC". In a realistic setting, we do not know the distribution of sources and the form of the channel, precisely. The distribution of sources might be non-uniform. In order to treat such a case, we have to make a code whose performance does not depend on the distribution of sources and the form of the channel. The performance of such a code should depend only on the correlation between input and outputs. Although the transmission rates are characterized by the pair (R_0, R_1), in order to make a code achieving the capacity region, we employ other two parameters R_c and R_p that satisfy $R_0 \leq R_\mathrm{c}$ and $R_0 + R_1 \leq R_\mathrm{c} + R_\mathrm{p}$. Hence, in the following definition of a universally attainable quadruple of exponents and equivocation rate, we focus on the set $(\mathbf{R}^+)^4$ of four real numbers $R_\mathrm{p}, R_\mathrm{c}, R_0, R_1$.

Definition 5: A set of functions $(\tilde{E}^b,\ \tilde{E}^e,\ \tilde{E}_+,\ \tilde{E}_-)$ from $(\mathbf{R}^+)^4 \times \mathcal{W}(\mathcal{X},\ \mathcal{Y},\ \mathcal{Z})$ to $[\mathbf{R}^+ \cup \{0\}]^4$ is said to be a universally attainable quadruple of exponents and equivocation rate for the family $\mathcal{W}(\mathcal{X},\ \mathcal{Y},\ \mathcal{Z})$ if there exist a sufficiently small real number $\delta > 0$ and a sufficiently large integer N satisfying the following condition for $R_\mathrm{p} > 0$, $R_\mathrm{c} > 0$, $\epsilon > 0$, $(R_0, R_1) \in (\mathbf{R}^+)^2$. For a given sequence of confidential message sets $\mathcal{S}_n$ with cardinality e^{nR_1} and the common message sets $\mathcal{E}_n$ with cardinality e^{nR_0}, there exists a sequence of codes Φ_n of length n of rates at least (R_0, R_1) such that

$$P_b[W^n, \Phi_n] \le \exp(-n[\tilde{E}^b(R_\mathrm{p}, R_\mathrm{c}, R_0, R_1, W) - \epsilon]), \tag{4}$$

$$P_e[W^n, \Phi_n] \le \exp(-n[\tilde{E}^e(R_\mathrm{p}, R_\mathrm{c}, R_0, R_1, W) - \epsilon]), \tag{5}$$

and

$$\begin{aligned} & I(S_n : Z^n)[W^n, \Phi_n] \\ & \le \max\{\exp(-n[\tilde{E}^{\mathcal{I}}_+(R_\mathrm{p}, R_\mathrm{c}, R_0, R_1, W) - \epsilon]), \\ & \qquad n[\tilde{E}^{\mathcal{I}}_-(R_\mathrm{p}, R_\mathrm{c}, R_0, R_1, W) + \epsilon]\}, \end{aligned} \tag{6}$$

for any sequence of joint distributions for confidential message S_n on $\mathcal{S}_n$ and the common message E_n on $\mathcal{E}_n$, and the n-th memoryless extension of any channel $W \in \mathcal{W}(\mathcal{X}, \mathcal{Y}, \mathcal{Z})$ and $n \ge N$.

In order to describe the exponential decreasing rate, as in [11], we introduce the following functions.

$$\begin{aligned} & \phi(\rho, P_{Z|L}, P_L) \\ & = \log \sum_z \left(\sum_\ell P_L(\ell)(P_{Z|L}(z|\ell)^{1/(1-\rho)}) \right)^{1-\rho}, \end{aligned} \tag{7}$$

$$\begin{aligned} & \phi(\rho, P_{Z|V}, P_{V|U}, P_U) \\ & = \log \sum_u P_U(u) \sum_z \left(\sum_v P_{V|U}(v|u)(P_{Z|V}(z|v)^{1/(1-\rho)}) \right)^{1-\rho}. \end{aligned}$$

Observe that ϕ is essentially Gallager's function E_0 [7]. Using these quantities, we define

$$\begin{aligned} & \tilde{E}^b(R_\mathrm{p}, R_\mathrm{c}, P_{Y,V,U}) \\ & := \max_{0 \le \rho \le 1} \min[-\rho R_p - \phi(-\rho, P_{Y|V}, P_{V|U}, P_U), \\ & \qquad - \rho(R_p + R_c) - \phi(-\rho, P_{Y|U,V}, P_{V,U})] \end{aligned} \tag{8}$$

and

$$\tilde{E}^e(R_\mathrm{c}, P_{Z,U}) := \max_{0 \le \rho \le 1} -\rho R_c - \phi(-\rho, P_{Z|U}, P_U) \tag{9}$$

$$\tilde{E}^\phi(R, P_{Z,V,U}) := \max_{0 \le \rho \le 1} \rho R - \phi(\rho, P_{Z|V}, P_{V|U}, P_U). \tag{10}$$

Suppose that we are given a broadcast $W : \mathcal{X} \to \mathcal{Y}, \mathcal{Z}$ and positive real numbers R_p and R_c. We fix a distribution Q_{UV} on $\mathcal{U} \times \mathcal{V}$, a channel $\Xi : \mathcal{V} \to \mathcal{X}$ and the rates $(R_\mathrm{p}, R_\mathrm{c}, R_0, R_1) \in (\mathbf{R}^+)^4$, where the RVs U ,V, X, Y and Z are distributed according to Q_{UV}, Ξ and W. We present a universally attainable quadruple of exponents and leaked information rate in terms of R_p, R_c, Q_{UV} and Ξ as

$$E^b = E^b(R_\mathrm{p}, R_\mathrm{c}, R_0, R_1, W) = \tilde{E}^b(R_\mathrm{p}, R_\mathrm{c}, (W \circ \Xi) \cdot Q_{UV}), \tag{11}$$

$$E^e = E^e(R_\mathrm{p}, R_\mathrm{c}, R_0, R_1, W) = \tilde{E}^e(R_\mathrm{c}, (W \circ \Xi) \cdot Q_{UV}), \tag{12}$$

$$E^{\mathcal{I}}_+ = E^{\mathcal{I}}_+(R_\mathrm{p}, R_\mathrm{c}, R_0, R_1, W) = \tilde{E}^\phi(R_\mathrm{p} - R_1, (W \circ \Xi) \cdot Q_{UV}), \tag{13}$$

$$E^{\mathcal{I}}_- = E^{\mathcal{I}}_-(R_\mathrm{p}, R_\mathrm{c}, R_0, R_1, W) = I(V; Z|U) - R_\mathrm{p} + R_1. \tag{14}$$

Theorem 6 (Extension of [17, Theorem 1, part (a)]): Eqs. (11)–(14) are source-channel universally attainable rates of exponents and equivocation rate in the sense of Definition 5.

The proof will be given in Section X after the proof of universal code for SMC.

Remark 7: Csiszár and Körner[5] treated BCC with non-uniform information source. However, their formulation is different from our formulation in the following point. In their formulation, they fixed a correlated non-uniform information source on $\mathcal{S} \times \mathcal{E}$ and assume that the information source S_n and E_n obey its n-fold independent and identical distribution. However, in our formulation, we do not assume the independent and identical distribution condition for the distribution of the information source S_n and E_n. Further, our universal code does not depend on the distribution of sources. Indeed, information source is not given as an independent and identical distribution or known, in general. So, our setting is needed for such a case.

III. BROADCAST CHANNELS WITH DEGRADED MESSAGE SETS

If we set $R_e = 0$ in the BCC, the secrecy requirement is removed from BCC, and the coding problem is equivalent to the broadcast channel with degraded message sets (abbreviated as BCD) considered by Körner and Marton [16].

Corollary 8: The capacity region of the BCD is given by the pair of the rate of common message R_c and the rate of private message R_p such that there exists a Markov chain $U \to V = X \to YZ$ and

$$\begin{aligned} R_\mathrm{c} & \le \min[I(U;Y), I(U;Z)], \\ R_\mathrm{c} + R_\mathrm{p} & \le I(V;Y|U) + \min[I(U;Y), I(U;Z)]. \end{aligned}$$

Now, we give a code that attains the rate pair satisfies

$$R_\mathrm{c} < \min[I(U;Y), I(U;Z)], \ R_\mathrm{p} < I(V;Y|U). \tag{15}$$

For a given Markov chain $U \to V \to X \to YZ$, we construct an ensemble of codes by the following random coding. For any element $s_\mathrm{c} \in \mathcal{S}_c$, $\Phi_c(s_\mathrm{c})$ is the random variable taking values in $\mathcal{U}$, is subject to the distribution P_U, and is independent of $\Phi_c(s'_c)$ with $s'_c \ne s_c \in \mathcal{S}_c$. For any element $s_\mathrm{p} \in \mathcal{S}_p$, $\Phi_p(s_\mathrm{c}, s_\mathrm{p})$ is the random variable taking values in $\mathcal{V}$, and is subject to the distribution $P_{V|U=\Phi(s_c)}$, and is independent of $\Phi_p(s'_\mathrm{c}, s'_\mathrm{p})$ with $(s'_\mathrm{c}, s'_\mathrm{p}) \ne (s_\mathrm{c}, s_\mathrm{p})$. Bob's decoder Φ_b and Eve's decoder Φ_e are defined as the maximum likelihood decoders. The quadruple $(\Phi_c, \Phi_p, \Phi_b, \Phi_e)$ is simplified to Φ.

Lemma 9: [14, Section IV.B] The above ensemble of codes Φ satisfies the following inequalities.

$$\begin{aligned} \mathrm{E}_\Phi P_b[P_{Y|V}, \Phi] \le & |\mathcal{S}_\mathrm{p}|^\rho e^{\phi(-\rho, P_{Y|V}, P_{V|U}, P_U)} \\ & + (|\mathcal{S}_\mathrm{c}||\mathcal{S}_\mathrm{p}|)^\rho e^{\phi(-\rho, P_{Y|U,V}, P_{U,V})} \end{aligned} \tag{16}$$

$$\mathrm{E}_\Phi P_e[P_{Z|V}, \Phi] \le |\mathcal{S}_\mathrm{c}|^\rho e^{\phi(-\rho, P_{Z|U}, P_U)}. \tag{17}$$

Markov inequality guarantees that there exists a code Φ such that

$$P_b[P_{Y|V}, \Phi] \le 2|\mathcal{S}_\mathrm{p}|^\rho e^{\phi(-\rho, P_{Y|V}, P_{V|U}, P_U)} + 2(|\mathcal{S}_\mathrm{c}||\mathcal{S}_\mathrm{p}|)^\rho e^{\phi(-\rho, P_{Y|U,V}, P_{U,V})}$$

$$P_e[P_{Z|V}, \Phi] \le 2|\mathcal{S}_\mathrm{c}|^\rho e^{\phi(-\rho, P_{Z|U}, P_U)}.$$

That is, there exists sequence of codes Φ_n with the rate of common message R_c and the rate of private message R_p of length n such that

$$\begin{aligned} P_b[P^n_{Y|V}, \Phi_n] \le & 2e^{n(\rho R_p + \phi(-\rho, P_{Y|V}, P_{V|U}, P_U))} \\ & + 2e^{n(\rho(R_p + R_c) + \phi(-\rho, P_{Y|U,V}, P_{U,V}))} \end{aligned} \tag{18}$$

$$P_e[P^n_{Z|V}, \Phi_n] \le 2e^{n(\rho R_c + \phi(-\rho, P_{Z|U}, P_U))}. \tag{19}$$

The above values go to zero with the exponents $\tilde{E}^b(R_{\mathrm{p}}, R_{\mathrm{c}}, P_{Y,V,U})$ and $\tilde{E}^e(R_{\mathrm{c}}, P_{Z,U})$. The condition (15) guarantees that both exponents are positive. In particular, Körner and Sgarro [17] provided the code that universally attains the above exponent in the following way. Assume that P_{U^n,V^n} be the uniform distribution on the sets of sequences of length n whose joint type is $Q_{U,V}$. When we generate our code by the above random coding according to the joint distribution P_{U^n,V^n}, both error probabilities satisfy the following inequalities with probability $\frac{13}{16}$.

$$P_b[P^n_{Y|V}, \Phi_n] \le \exp(-n[\tilde{E}^b(R_{\mathrm{p}}, R_{\mathrm{c}}, Q_{U,V}) - \delta]), \tag{20}$$

$$P_e[P^n_{Z|V}, \Phi_n] \le \exp(-n[\tilde{E}^e(R_{\mathrm{c}}, Q_{U,V}) - \delta]), \tag{21}$$

IV. General channel resolovability

In the wire-tap channel model, when the dummy message obeys the uniform distribution, channel resolovability[8], [10] works for guaranteeing the security. In this paper, we consider the secrecy when the dummy message does not obey the uniform distribution. In such a case, the channel resolovability does not work properly. Hence, we need a generalization of channel resolovability.

Assume that a channel $W(y|x)$ from the alphabet X to be sent to the output data Y is given. For a fixed distribution p for X, we focus on the average output distribution $W_p(y) := \sum_x p(x)W(y|x)$ and an encoder Λ from the message A to the alphabet X. This purpose is approximating the average output distribution $W_p(y) := \sum_x p(x)W(y|x)$ by the output distribution with input $\Lambda(A)$. In the original channel resolovability, we cosider how well the average output distribution W_p can be approximated with a restricted cardinality of the message set when the message A obeys the uniform distribution. In the following, we consider this approximation problem when the message A does not obey the uniform distribution, and we call this approximation problem general channel resolovability, which is essential for secure multiplex coding with a common message with dependent and non-uniform messages.

Now, we apply the random coding to the alphabet A with the probability distribution p. For $a \in \mathcal{A}$, $\Lambda(a)$ is the random variable subject to the distribution p on $\mathcal{X}$. For $a \neq a' \in \mathcal{A}$, $\Lambda(a)$ is independent of $\Lambda(a')$. Then, $\Lambda := \{\Lambda(a)\}_{a\in\mathcal{A}}$ gives the map from $\mathcal{A}$ to $\mathcal{X}$ as $a \mapsto \Lambda(a)$. For a distribution P^A on $\mathcal{A}$, we can define

$$\begin{aligned}
\psi(\rho|Q\|P) &:= \log \sum_a Q(a)^{1+s} P(a)^{-\rho} \\
\psi(\rho|W,p) &:= \log \sum_x p_x e^{\psi(\rho|W_x\|W_p)} \\
H_{1+\rho}(A) &:= -\frac{1}{\rho} \log \sum_a P^A(a)^{1+s} \\
H_{1+\rho}(A|B) &:= -\frac{1}{\rho} \log \sum_{a,b} P^B(b) P^{A|B}(a|b)^{1+s}.
\end{aligned}$$

$H_1(A)$ and $H_1(A|B)$ are defined to be $H(A)$ and $H(A|B)$. Since $\rho \mapsto \rho H_{1+\rho}(A), \rho H_{1+\rho}(A|B)$ are concave and $0H_{1+0}(A) = 0H_{1+0}(A|B) = 0$,

$$H_{1+\rho}(A) \ge H_{1+\rho'}(A) \tag{22}$$

$$H_{1+\rho}(A|B) \ge H_{1+\rho'}(A|B) \tag{23}$$

for $0 \le \rho \le \rho'$.

Then, we have the following theorem:

Theorem 10 (General channel resolvability): For $\rho \in (0, 1]$, we obtain

$$\mathrm{E}_\Lambda e^{\rho D(W_{P^A \circ \Lambda^{-1}}\|W_p)} \le \mathrm{E}_\Lambda e^{\psi(\rho|W_{P^A \circ \Lambda^{-1}}\|W_p)} \le 1 + e^{-\rho H_{1+\rho}(A)} e^{\psi(\rho|W,p)}.$$

By applying Jensen inequality to the function $x \mapsto e^x$, Theorem 10 yields

$$\begin{aligned}
&\mathrm{E}_\Lambda D(W_{P^A \circ \Lambda^{-1}}\|W_p) \le \frac{1}{\rho} \log \mathrm{E}_\Lambda e^{\rho D(W_{P^A \circ \Lambda^{-1}}\|W_p)} \\
\le&\frac{1}{\rho} \log(1 + e^{-\rho H_{1+\rho}(A)} e^{\psi(\rho|W,p)}),
\end{aligned}$$

which is non-uniform generalization of [10, Lemma 2]. This theorem will be used for the proof of Theorem 17.

Proof: Since $s \mapsto \psi(s|W_{P^A \circ \Lambda^{-1}}\|W_p)$ is convex and $\psi(0|W_{P^A \circ \Lambda^{-1}}\|W_p) = 0$,

$$sD(W_{P^A \circ \Lambda^{-1}}\|W_p) \le \psi(s|W_{P^A \circ \Lambda^{-1}}\|W_p).$$

Thus,

$$\begin{aligned}
&\mathrm{E}_\Lambda e^{\psi(\rho|W_{P^A \circ \Lambda^{-1}}\|W_p)} = \mathrm{E}_\Lambda \sum_y (\sum_a P^A(a) W_{\Lambda(a)}(y))^{1+\rho} W_p^{-\rho}(y) \\
=&\mathrm{E}_\Lambda \sum_y (\sum_a P^A(a) W_{\Lambda(a)}(y))(\sum_{a'} P^A(a') W_{\Lambda(a')}(y))^\rho W_p^{-\rho}(y) \\
=&\sum_y \sum_a \Big(\mathrm{E}_{\Lambda(a)} P^A(a) W_{\Lambda(a)}(y) \mathrm{E}_{\Lambda|\Lambda(a)} (P^A(a) W_{\Lambda(a)}(y) \\
&\quad + \sum_{a' \neq a} P^A(a') W_{\Lambda(a')}(y))^\rho W_p^{-\rho}(y)\Big) \\
\le&\sum_y \sum_a \Big(\mathrm{E}_{\Lambda(a)} P^A(a) W_{\Lambda(a)}(y) (P^A(a) W_{\Lambda(a)}(y) \\
&\quad + \mathrm{E}_{\Lambda|\Lambda(a)} \sum_{a' \neq a} P^A(a') W_{\Lambda(a')}(y))^\rho W_p^{-\rho}(y)\Big) \qquad (24) \\
=&\sum_y \sum_a \Big(\mathrm{E}_{\Lambda(a)} P^A(a) W_{\Lambda(a)}(y) (P^A(a) W_{\Lambda(a)}(y) \\
&\quad + \sum_{a' \neq a} P^A(a') W_p(y))^\rho W_p^{-\rho}(y)\Big) \\
\le&\sum_y \sum_a \Big(\mathrm{E}_{\Lambda(a)} P^A(a) W_{\Lambda(a)}(y) (P^A(a) W_{\Lambda(a)}(y) \\
&\quad + W_p(y))^\rho W_p^{-\rho}(y)\Big) \qquad (25) \\
\le&\sum_y \sum_a \mathrm{E}_{\Phi(a)} P^A(a) W_{\Lambda(a)}(y) (P^A(a)^\rho W_{\Lambda(a)}(y)^\rho + W_p(y)^\rho) W_p^{-\rho}(y) \\
&\qquad (26) \\
=&\sum_y \sum_a \mathrm{E}_{\Lambda(a)} P^A(a) W_{\Lambda(a)}(y) (1 + P^A(a)^\rho W_{\Lambda(a)}(y)^\rho W_p^{-\rho}(y)) \\
=&1 + \sum_y \sum_a \mathrm{E}_{\Lambda(a)} P^A(a)^{1+\rho} W_{\Lambda(a)}(y)^{1+\rho} W_p^{-\rho}(y)) \\
=&1 + \sum_a P^A(a)^{1+\rho} \sum_y \sum_x p_x W_x(y)^{1+\rho} W_p^{-\rho}(y)) \\
=&1 + (\sum_a P^A(a)^{1+\rho}) e^{\psi(\rho|W,p)}.
\end{aligned}$$

In the above derivation, (24) follows from the concavity of $x \mapsto x^\rho$, (25) follows from $\sum_{a' \neq a} P^A(a') \le 1$, (26) follows from the inequality $(x + y)^\rho \le x^\rho + y^\rho$. ■

Next, in order to reduce the complexity, we consider the case when $\mathcal{X}$ and $\mathcal{A}$ are Abelian groups. We focus on the following condition for the ensemble for injective homomorphisms F from $\mathcal{A}$ to $\mathcal{X}$.

Condition 11: Any elements $x \neq 0 \in \mathcal{X}$ and $a \neq 0 \in \mathcal{A}$, the relation $F(a) = x$ holds with probability at most $\frac{1}{|\mathcal{X}|-1}$.

When $\mathcal{X}$ and $\mathcal{A}$ are vector spaces of a finite field $\mathbb{F}_q$, the set of all injective morphisms from $\mathcal{A}$ to $\mathcal{X}$ satisfies Condition 11.

We choose another random variable $G \in \mathcal{X}$ obeys the uniform distribution on $\mathcal{X}$ that is independent of the choice of $f_{\mathbf{X}}$. Then, we define a map $\Lambda_{F,G}(a) := F(a) + G$ and have the following theorem:

Theorem 12 (Affine channel resolvability): Under the above choice, we obtain

$$\begin{aligned}&\mathrm{E}_{F,G} e^{\rho D(W_{P^A \circ \Lambda_{F,G}^{-1}} \| W_{P_{\mathrm{mix}}})} \le \mathrm{E}_{F,G} e^{\psi(\rho | W_{P^A \circ \Lambda_{F,G}^{-1}} \| W_{P_{\mathrm{mix}}})} \\ \le & 1 + e^{-\rho H_{1+\rho}(A|Q)} e^{\psi(\rho|W,P_{\mathrm{mix}})}. \end{aligned} \tag{27}$$

This theorem will be used for the proof of Lemma 15, which is essential for the proof of Theorem 16.

Proof: We introduce the random variable $Z_a := \Lambda_{F,G}(a) = F(a)+G$. The random variable Z_a is independent of the choice of F. For $a' \in \mathcal{A}$, $\Lambda_{F,G}(a') = F(a'-a) + Z_a$. Since $(|\mathcal{X}|-1)\mathrm{E}_{F|Z_a} W_{\Lambda_{F,G}(a)} = (|\mathcal{X}|-1)\mathrm{E}_F W_{F(a'-a)+Z_a} \le \sum_x W_x = |\mathcal{X}| W_{P_{\mathrm{mix}}}$ for $a \in \mathcal{A}$, we obtain $\mathrm{E}_{F|Z_a} W_{\Lambda_{F,G}(a)} \le \frac{|\mathcal{X}|}{|\mathcal{X}|-1} W_{P_{\mathrm{mix}}}$ for $a \in \mathcal{A}$. Further, since $x \mapsto x^\rho$ is concave and $\sum_a P^A(a)^2 \ge \frac{1}{|\mathcal{A}|} \ge \frac{1}{|\mathcal{X}|}$, we obtain

$$\sum_a P^A(a) (\frac{1-P^A(a)}{1-1/|\mathcal{X}|})^\rho \le (\frac{1-\sum_a P^A(a)^2}{1-1/|\mathcal{X}|})^\rho \le (\frac{1-1/|\mathcal{X}|}{1-1/|\mathcal{X}|})^\rho = 1. \tag{28}$$

Our proof of Theorem 10 can be applied to our proof of Theorem 12 by replacing $\Lambda(a)$, $\Lambda|\Lambda(a)$, and P^X by Z_a, $F|Z_a$ and P_{mix}. Then, we obtain

$$\begin{aligned}
&\mathrm{E}_{F,G} e^{\psi(\rho | W_{P^A \circ \Lambda_{F,G}^{-1}} \| W_{P_{\mathrm{mix}}})} \\
\le & \sum_y \sum_a \Big(\mathrm{E}_{Z_a} P^A(a) W_{\Lambda_{F,G}(a)}(y) (P^A(a) W_{\Lambda_{F,G}(a)}(y) \\
& + \mathrm{E}_{F|Z_a} \sum_{a' \neq a} P^A(a') W_{\Lambda_{F,G}(a')}(y))^\rho W_{P_{\mathrm{mix}}}^{-\rho}(y) \Big) \\
= & \sum_y \sum_a \Big(\mathrm{E}_{Z_a} P^A(a) W_{Z_a}(y) (P^A(a) W_{Z_a}(y) \\
& + \frac{|\mathcal{X}|}{|\mathcal{X}|-1} \sum_{a' \neq a} P^A(a') W_{P_{\mathrm{mix}}}(y))^\rho W_{P_{\mathrm{mix}}}^{-\rho}(y) \Big) \\
= & \sum_y \sum_a \Big(\mathrm{E}_{Z_a} P^A(a) W_{Z_a}(y) (P^A(a) W_{Z_a}(y) \\
& + \frac{1-P^A(a)}{1-1/|\mathcal{X}|} W_{P_{\mathrm{mix}}}(y))^\rho W_{P_{\mathrm{mix}}}^{-\rho}(y) \Big) \\
\le & \sum_y \sum_a \Big(\mathrm{E}_{Z_a} P^A(a) W_{Z_a}(y) (P^A(a)^\rho W_{Z_a}(y)^\rho \\
& + (\frac{1-P^A(a)}{1-1/|\mathcal{X}|})^\rho W_{P_{\mathrm{mix}}}(y)^\rho) W_{P_{\mathrm{mix}}}^{-\rho}(y) \Big) & (29) \\
= & \sum_y \sum_a \Big(\mathrm{E}_{Z_a} P^A(a) W_{Z_a}(y) ((\frac{1-P^A(a)}{1-1/|\mathcal{X}|})^\rho \\
& + P^A(a)^\rho W_{Z_a}(y)^\rho W_{P_{\mathrm{mix}}}^{-\rho}(y)) \Big) \\
= & \sum_a P^A(a) (\frac{1-P^A(a)}{1-1/|\mathcal{X}|})^\rho \\
& + \sum_y \sum_a \mathrm{E}_{Z_a} P^A(a)^{1+\rho} W_{Z_a}(y)^{1+\rho} W_{P_{\mathrm{mix}}}^{-\rho}(y)) \\
= & \sum_a P^A(a) (\frac{1-P^A(a)}{1-1/|\mathcal{X}|})^\rho \\
& + \sum_a P^A(a)^{1+\rho} \sum_y \sum_x p_x W_x(y)^{1+\rho} W_{P_{\mathrm{mix}}}^{-\rho}(y)) \\
\le & 1 + (\sum_a P^A(a)^{1+\rho}) e^{\psi(\rho|W,P_{\mathrm{mix}})}. & (30)
\end{aligned}$$

In the above derivation, (25) follows from $\sum_{a' \neq a} P^A(a') \le 1$, (29) follows from the inequality $(x+y)^\rho \le x^\rho + y^\rho$. The final inequality follows from (28). ■

In the following, we assume that the input probability space $\mathcal{X}$ is an Abelian group, and an action of $\mathcal{X}$ to the output probability space $\mathcal{Y}$ is given. When a channel W from $\mathcal{X}$ to $\mathcal{Y}$ is regular in the sense of Delsarte-Piret [6], if there is a probability distribution P_Y such that

$$W_x(y) = P_Y(x \cdot y).$$

Since a regular channel W satisfies

$$D(W_{P^A \circ \Lambda_{F,G}^{-1}} \| W_{P_{\mathrm{mix}}}) = D(W_{P^A \circ \Lambda_{F,G'}^{-1}} \| W_{P_{\mathrm{mix}}})$$

for any $G, G' \in \mathcal{X}$, we obtain the following corollary. That is, this corollary implies that we need the additional random variable G is not needed in the regular case.

Corollary 13: When the channel W is a regular channel


S_0
common message
$S_1, \dots, S_T$
multiple secret messages
randomly chosen but fixed isomorphism F'
$+ \leftarrow G'$
(B_1, B_2)
$(S_0, \; B_1)$
common message for BCD encoder
B_2
private message for BCD encoder
Encoder for BCD (broadcast channel with degraded message sets)
$\Phi_c(S_0, B_1) \sim P_U$
(not sent)
$\Phi_p(\Phi_c(S_0, B_1), B_2) \sim P_V$
artificial channel $P_{X|V}$
physical channel $P_{YZ|X}$
Bob
$Y \leftarrow$
Z
Eve

Fig. 1. Communication structure used in Sections V–IX

given by a distribution P on $\mathcal{Y}$, we obtain

$$\begin{aligned} & \mathrm{E}_F e^{\rho D(W_{P^{A \circ \Lambda_{F,G}^{-1}}} \| W_{P_{\mathrm{mix}}})} \\ \le & \mathrm{E}_F e^{\psi(\rho | W_{P^{A \circ \Lambda_{F,G}^{-1}}} \| W_{P_{\mathrm{mix}}})} \\ \le & 1 + e^{-\rho H_{1+\rho}(A|Q)} e^{\psi(\rho | W, P_{\mathrm{mix}})}. \end{aligned} \tag{31}$$

for any $G \in \mathcal{X}$.

V. SECURE MULTIPLEX CODING WITH A COMMON MESSAGE: NON-ASYMPTOTIC SETTING

In the following, we treat secure multiplex coding with a common message. In this section, we give the formulation of secure multiplex coding with a common message. After the formulation, we give two kinds of random construction of codes for secure multiplex coding with a common message and the evaluation of their performance in the non-asymptotic setting.

A. Formulation and preparation

In secure multiplex coding with a common message, Alice sends the common message S_0 to Bob and Eve, and T secret messages $S_1, \dots, S_T$ to Bob. We do not necessarily assume the uniformity for the distributions of messages $S_0, S_1, \dots, S_T$. Hence, there might exist statistical correlations among messages $S_0, S_1, \dots, S_T$. In this scenario, Alice and Bob can use $S_1, \dots, S_{i-1}$, $S_{i+1}, \dots, S_T$ for random bits making S_i ambiguous to Eve. When we focus on $S_{\mathcal{I}} := (S_i : i \in \mathcal{I})$ for $\mathcal{I} \subset \{1, \dots, T\}$, the remaining information $S_{\mathcal{I}^c}$ is used for random bits making $S_{\mathcal{I}}$ ambiguous to Eve. These messages are assumed to belongs to the sets $\mathcal{S}_0, \mathcal{S}_1, \dots, \mathcal{S}_T$. Our protocol is given by Alice's stochastic encoder φ_a from $\mathcal{S} \times \mathcal{E}$ to $\mathcal{X}$, Bob's deterministic decoder $\varphi_b : \mathcal{Y} \to \mathcal{S} \times \mathcal{E}$ and Eve's deterministic decoder $\varphi_e : \mathcal{Z} \to \mathcal{E}$. The triple $\varphi = (\varphi_a, \varphi_b, \varphi_e)$ is called a code for broadcast channels with confidential messages. Then, the performance is evaluated by the following quantities. (1) The sizes of the sets of the common messages and all of the secret messages, i.e, $|\mathcal{S}_0|, |\mathcal{S}_1|, \dots, |\mathcal{S}_T|$. (2) Bob's decoding error probability $P_b[P_{Y|X}, \varphi] := \Pr\{(S_0, S_1, \dots, S_T) \neq \varphi_b(Y)\}[P_{Y|X}, \varphi]$. (3) Eve's decoding error probability $P_e[P_{Y|X}, \varphi] := \Pr\{S_0 \neq \varphi_e(Z)\}[P_{Z|X}, \varphi]$. (4) leaked information $I(S_{\mathcal{I}} : Z|S_0)[P_{Z|X}, \varphi_a]$. Instead of $I(S_{\mathcal{I}} : Z|S_0)[P_{Z|X}, \varphi_a]$, we sometimes treat (5) Eve's uncertainty $H(S_{\mathcal{I}}|Z, S_0)[P_{Z|X}, \varphi_a]$. However, when we treat the universality of our code, leaked information $I(S_{\mathcal{I}} :$

$Z|S_0)[P_{Z|X},\varphi_a]$ is used for criterion for performance of our code. So, we adopt leaked information $I(S_{\mathcal{I}}:Z|S_0)[P_{Z|X},\varphi_a]$ rather than Eve's uncertainty $H(S_{\mathcal{I}}|Z,S_0)[P_{Z|X},\varphi_a]$.

In order to guarantee that the leaked information is small, we employ the method of channel resolvability given in Section IV. In order to employ this method, we have to use the random coding method. In this section, we propose two kinds of random construction for our code. In Subsection V-B, we give the first construction, which, attains the capacity region defined in Section VI-B. This construction has two steps. In the first step, similar to the BCD encoder, we apply superposition random coding. In the second step, as is illustrated in Fig. 1, we split the confidential message into the private message B_2 and a part B_1 of the common message encoded by the BCD encoder. The coding scheme for BCC in [5] uses this kind of message splitting. The average leaked information under this kind of construction is evaluated by Theorem 12, which is a affine version of channel resolvability. In Subsection V-C, we give the second construction, which, realizes a better exponential decreasing rate for leaked information. However, it cannot realize the capacity region. The average leaked information under this kind of construction is evaluated by Theorem 10, which is a simple generalization of channel resolvability.

Before giving two kinds of random construction of codes for secure multiplex coding with a common message, we prepare several useful facts. As in [11], we introduce the following functions, which are complicated version of $\psi(\rho|W,P)$:

$$\begin{aligned}&\psi(\rho,P_{Z|L},P_L)\\ =&\log\sum_z\sum_\ell P_L(\ell)P_{Z|L}(z|\ell)^{1+\rho}P_Z(z)^{-\rho}, \qquad (32)\\ &\psi(\rho,P_{Z|V},P_{V|U},P_U)\\ =&\log\sum_u P_U(u)\sum_v P_{V|U}(v|u)\sum_z P_{Z|V}(z|v)^{1+\rho}P_{Z|U}(z|u)^{-\rho}, \qquad (33)\end{aligned}$$

Proposition 14: [7], [11] $\exp(\phi(\rho,P_{Z|L},P_L))$ is concave with respect to P_L with fixed $0<\rho<1$ and $P_{Z|L}$. For fixed $0<\rho<1$, P_L and $P_{Z|L}$ we have

$$\exp(\psi(\rho,P_{Z|L},P_L))\le\exp(\phi(\rho,P_{Z|L},P_L)). \qquad (34)$$

$$\exp(\phi(\rho,P_{Z|L},P_L))\le C_1\exp(\phi(\rho,P_{Z|L},\tilde{P}_L)) \qquad (35)$$

when $P_L\le C_1\tilde{P}_L$.
For a fixed code Φ, any distribution $\tilde{P}_Z$ on Z satisfies

$$\begin{aligned}&\rho I(S_{\mathcal{I}}:Z|S_0)[P_{Z|V},\Phi]\\ =&\rho\sum_{s_0}P_{S_0}(s_0)I(S_{\mathcal{I}}:Z|S_0=s_0)[P_{Z|V},\Phi]\\ =&\rho\sum_{s_0}P_{S_0}(s_0)\sum_{s_{\mathcal{I}}}P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0)D(P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi}\|P_{Z|S_0=s_0,\Phi})\\ \le&\sum_{s_0}P_{S_0}(s_0)\sum_{s_{\mathcal{I}}}P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0)\rho D(P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi}\|\tilde{P}_Z) \qquad (36)\end{aligned}$$

and

$$\rho D(P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi}\|\tilde{P}_Z)\le\psi(\rho|P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi}\|\tilde{P}_Z). \qquad (37)$$

Thus, Jensen inequality yields that

$$\begin{aligned}&e^{\rho I(S_{\mathcal{I}}:Z|S_0)[P_{Z|V},\Phi]}\le e^{\sum_{s_0}P_{S_0}(s_0)\sum_{s_{\mathcal{I}}}P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0)\rho D(P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi}\|\tilde{P}_Z)}\\ \le&\sum_{s_0}P_{S_0}(s_0)\sum_{s_{\mathcal{I}}}P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0)e^{D\rho(P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi}\|\tilde{P}_Z)} \qquad (38)\\ \le&\sum_{s_0}P_{S_0}(s_0)\sum_{s_{\mathcal{I}}}P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0)e^{\psi(\rho|P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi}\|\tilde{P}_Z)}. \qquad (39)\end{aligned}$$

B. First construction

First, we give the first kind of random coding for SMC as follows.

Construction 1: For a given Markov chain $U\to V\to X\to YZ$, we introduce two random variables B_1 and B_2 that take values in modules $\mathcal{B}_1$ and $\mathcal{B}_2$ and are subject to the uniform distribution. We give the following random coding by assuming that $\mathcal{S}_1,\ldots,\mathcal{S}_T$ have a module structure. For any element $(s_0,b_1)\in\mathcal{S}_0\times\mathcal{B}_1$, we define the random variable $\Phi_c(s_0,b_1)\in\mathcal{U}$ that is subject to the distribution P_U and is independent of $\Phi_c(s_0',b_1')$ with $(s_0',b_1')\neq(s_0,b_1)\in\mathcal{S}_0\times\mathcal{B}_1$. For any element $(\Phi_c(s_0,b_1),b_2)\in\mathcal{U}\times\mathcal{B}_2$, we define another random variable $\Phi_p(\Phi_c(s_0,b_1),b_2)\in\mathcal{V}$ that is subject to the distribution $P_{V|U=\Phi_c(s_0,b_1)}$ and is conditionally independent of $\Phi_p(\Phi_c(s_0,b_1),b_2')$ with $b_2'\neq b_2$ given $\Phi_c(s_0,b_1)$. Next, based on the code $\Phi_a=(\Phi_c,\Phi_p)$, we choose an ensemble for isomorphisms F' from $\mathcal{S}_1\times\cdots\times\mathcal{S}_T$ to $\mathcal{B}_1\times\mathcal{B}_2$ as modules satisfying Condition 11. We choose the random variable $G'\in\mathcal{B}_1\times\mathcal{B}_2$ that obeys the uniform distribution on $\mathcal{B}_1\times\mathcal{B}_2$ that is independent of the choice of F'. Then, we define a map $\Lambda_{F',G'}(s):=F'(s)+G'$ and have the following lemma: Combining the above three codes, we construct the code $\tilde{\Phi}_a=(\Phi_a,\Lambda_{F',G'}):\mathcal{S}_0\times\mathcal{S}_1\times\cdots\times\mathcal{S}_T\to\mathcal{U}\times\mathcal{V}$. Similar to the case of BCD, Bob's decoder Φ_b and Eve's decoder Φ_e are defined as the maximum likelihood decoders. Hence, our code is written by the triple $(\tilde{\Phi}_a,\Phi_b,\Phi_e)$. The structure of encoder is illustrated in Fig. 1.

In order to evaluate the averaged performance of the above code $(\tilde{\Phi}_a,\Phi_b,\Phi_e)$, we prepare the following lemma.

Lemma 15: When we fixed a code Φ_a for the BCD part, we obtain the following average performance.

$$\begin{aligned}&\mathrm{E}_{F',G'|\Phi_a}\exp(\rho I(S_{\mathcal{I}}:Z|S_0)[P_{Z|V},(\Phi_a,\Lambda_{F',G'})])\\ \le&\mathrm{E}_{F',G'|\Phi_a}\sum_{s_0}P_{S_0}(s_0)\sum_{s_{\mathcal{I}}}P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0)e^{\rho D(P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi_a}\|\tilde{P}_{Z|S_0=s_0,\Phi_a})}\\ \le&1+\sum_{s_0}P_{S_0}(s_0)\sum_{s_{\mathcal{I}}}P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0)e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0)}\\ &\qquad\cdot e^{\psi(\rho,P_{Z|B_1,B_2,S_0=s_0,\Phi_a},\bar{P}_{B_1,B_2})}, \qquad (40)\end{aligned}$$

where $\bar{P}_{B_1,B_2}$ is the uniform distribution on $\mathcal{B}_1\times\mathcal{B}_2$ and $\tilde{P}_{Z|S_0=s_0,\Phi_a}$ is the distribution of the channel output of the transmitted codeword $\Phi_p(\Phi_c(s_0,\bar{B}_1),\bar{B}_2)$ with $(\bar{B}_1,\bar{B}_2)$ obeying the uniform distribution $\bar{P}_{B_1,B_2}$. Further, due to Corollary 13, in the regular channel case, the inequalities (40) hold even when G' is a constant.

Applying Jensen's inequality for the convex function $x \mapsto e^x$ and the inequality $\log(1+x) \le x$, we obtain

$$\begin{aligned}
&\mathrm{E}_{F',G'|\Phi_a} \rho I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, (\Phi_a, \Lambda_{F',G'})] \\
\le & \log\Big(1 + \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}=s_{\mathcal{I}}, S_0=s_0)} \\
&\qquad \cdot e^{\psi(\rho, P_{Z|B_1,B_2,S_0=s_0,\Phi_a}, \bar{P}_{B_1,B_2})}\Big) \\
\le & \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}=s_{\mathcal{I}}, S_0=s_0)} \\
&\qquad \cdot e^{\psi(\rho, P_{Z|B_1,B_2,S_0=s_0,\Phi_a}, \bar{P}_{B_1,B_2})}.
\end{aligned} \tag{41}$$

Proof: Applying (38) to the case when $\tilde{P}_Z = \tilde{P}_{Z|S_0=s_0,\Phi_a}$, we obtain

$$\begin{aligned}
&\mathrm{E}_{F',G'|\Phi_a} e^{\rho I(S_{\mathcal{I}}:Z|S_0)[P_{Z|V},(\Phi_a,\Lambda_{F',G'})]} \\
\le & \mathrm{E}_{F',G'|\Phi_a} \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) e^{\rho D(P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi_a} \| \tilde{P}_{Z|S_0=s_0,\Phi_a})} \\
\le & \mathrm{E}_{F',G'|\Phi_a} \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) e^{\psi(\rho | P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi_a} \| \tilde{P}_{Z|S_0=s_0,\Phi_a})}.
\end{aligned} \tag{42}$$

For a fixed $s_{\mathcal{I}}$, we apply Theorem 12 to the case when $\mathcal{A}$ is $\mathcal{S}_{\mathcal{I}^c}$, $\mathcal{X}$ is $\mathcal{B}_1 \times \mathcal{B}_2$, G is $G' + F'(s_{\mathcal{I}}, 0)$, which is independent of F', and F is the map $s_{\mathcal{I}^c} \mapsto F'(0, s_{\mathcal{I}^c})$, which satisfies Condition 11. Then, $\Lambda_{F',G'}(s_{\mathcal{I}}, s_{\mathcal{I}^c}) = F'(s_{\mathcal{I}}, s_{\mathcal{I}^c}) + G' = F'(0, s_{\mathcal{I}^c}) + Z_{s_{\mathcal{I}}}$. Thus, we obtain

$$\begin{aligned}
&\mathrm{E}_{F',G'|\Phi_a} e^{\psi(\rho | P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi_a} \| \tilde{P}_{Z|S_0=s_0,\Phi_a})} \\
\le & 1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}=s_{\mathcal{I}}, S_0=s_0)} e^{\psi(\rho, P_{Z|B_1,B_2,S_0,\Phi_a}, \bar{P}_{B_1,B_2})}.
\end{aligned} \tag{43}$$

Thus, we obtain (40). ■

Using the above lemma, we obtain the following theorem, which gives the averaged performance of the above code $(\tilde{\Phi}_a, \Phi_b, \Phi_e)$. Due to this theorem, we will give the capacity region in Subsection VI-B.

Theorem 16: The above ensemble of codes $\Phi = (\tilde{\Phi}_a, \Phi_b, \Phi_e)$ satisfies the following inequalities

$$\begin{aligned}
&\mathrm{E}_{\tilde{\Phi}_a} \exp(\rho I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \tilde{\Phi}_a]) \\
\le & \mathrm{E}_{\tilde{\Phi}_a} \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) e^{\rho D(P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi_a} \| \tilde{P}_{Z|S_0=s_0,\Phi_a})} \\
\le & 1 + |\mathcal{B}_1|^\rho e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}, S_0) + \phi(\rho, P_{Z|V}, P_{V|U}, P_U)},
\end{aligned} \tag{44}$$

and

$$\mathrm{E}_\Phi P_b[P_{Y|V}, \Phi] \le |\mathcal{B}_2|^\rho e^{\phi(-\rho, P_{Y|V}, P_{V|U}, P_U)} + (|\mathcal{S}_0||\mathcal{S}|)^\rho e^{\phi(-\rho, P_{Y|U,V}, P_{U,V})} \tag{45}$$

$$\mathrm{E}_\Phi P_e[P_{Z|V}, \Phi] \le |\mathcal{S}_0|^\rho e^{\phi(-\rho, P_{Z|U}, P_U)}. \tag{46}$$

Further, due to Corollary 13, in the regular channel case, the inequalities (44) hold even when the random variable G' fixed.

Applying Jensen's inequality to the convex function $x \mapsto e^x$, we obtain

$$\begin{aligned}
&\mathrm{E}_{\tilde{\Phi}_a} \rho I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \tilde{\Phi}_a] \\
\le & \log(1 + |\mathcal{B}_1|^\rho e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}, S_0) + \phi(\rho, P_{Z|V}, P_{V|U}, P_U)}) \\
\le & |\mathcal{B}_1|^\rho e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}, S_0) + \phi(\rho, P_{Z|V}, P_{V|U}, P_U)}.
\end{aligned} \tag{47}$$

Markov inequality guarantees that there exists a code $\Phi = (\tilde{\Phi}_a, \Phi_b, \Phi_e)$ such that

$$\begin{aligned}
&\exp(\rho I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \tilde{\Phi}_a]) \\
\le & 2^{T+2} \inf_{0 \le \rho \le 1} (1 + |\mathcal{B}_1|^\rho e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}, S_0) + \phi(\rho, P_{Z|V}, P_{V|U}, P_U)}) \\
\le & 2^{T+3} e^{[\rho \log |\mathcal{B}_1| - \rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}, S_0) + \phi(\rho, P_{Z|V}, P_{V|U}, P_U)]_+},
\end{aligned} \tag{48}$$

$$\begin{aligned}
&I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \tilde{\Phi}_a] \\
\le & \inf_{0 \le \rho \le 1} \frac{2^{T+2}}{\rho} |\mathcal{B}_1|^\rho e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}, S_0) + \phi(\rho, P_{Z|V}, P_{V|U}, P_U)},
\end{aligned} \tag{49}$$

$$\begin{aligned}
&P_b[P_{Y|V}, \Phi] \\
\le & 2^{T+2} \inf_{0 \le \rho \le 1} (|\mathcal{S}|^\rho e^{\phi(-\rho, P_{Y|V}, P_{V|U}, P_U)} + |\mathcal{S}_0|^\rho e^{\phi(-\rho, P_{Y|U}, P_U)}),
\end{aligned} \tag{50}$$

$$\begin{aligned}
&P_e[P_{Z|V}, \Phi] \\
\le & 2^{T+2} \inf_{0 \le \rho \le 1} |\mathcal{S}_0|^\rho e^{\phi(-\rho, P_{Z|U}, P_U)}.
\end{aligned} \tag{51}$$

for all $\mathcal{I}$. Taking the logarithm in (48), we obtain

$$\begin{aligned}
&I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \tilde{\Phi}_a] \\
\le & \Big[\log |\mathcal{B}_1| + \frac{1}{\rho} \psi(\rho, P_{Z|V}, P_{V|U}, P_U) - H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}, S_0)\Big]_+ \\
&+ (T+3) \frac{\log 2}{\rho}.
\end{aligned} \tag{52}$$

Proof of Theorem 16:

We show (44). Using (34), we obtain

$$\begin{aligned}
&\mathrm{E}_{\Phi_a} e^{\psi(\rho, P_{Z|B_1,B_2,S_0,\Phi_a}, \bar{P}_{B_1,B_2})} \\
\le & \mathrm{E}_{\Phi_a} e^{\phi(\rho, P_{Z|B_1,B_2,S_0,\Phi_a}, \bar{P}_{B_1,B_2})} && (53) \\
= & \mathrm{E}_{\Phi_a} \sum_z (\sum_{b_1,b_2} P_{B_1,B_2}(b_1,b_2) P_{Z|B_1,B_2,S_0,\Phi_a}(z|b_1,b_2)^{\frac{1}{1-\rho}})^{1-\rho} \\
= & \mathrm{E}_{\Phi_c} \mathrm{E}_{\Phi_p|\Phi_c} \sum_z (\sum_{b_1,b_2} \frac{1}{|\mathcal{B}_1||\mathcal{B}_2|} P_{Z|V}(z|\Phi_p(s_0,b_1,b_2))^{\frac{1}{1-\rho}})^{1-\rho} \\
\le & \mathrm{E}_{\Phi_c} \sum_z (\mathrm{E}_{\Phi_p|\Phi_c} \sum_{b_1,b_2} \frac{1}{|\mathcal{B}_1||\mathcal{B}_2|} P_{Z|V}(z|\Phi_p(s_0,b_1,b_2))^{\frac{1}{1-\rho}})^{1-\rho} && (54) \\
= & \mathrm{E}_{\Phi_c} \sum_z (\sum_{b_1,b_2} \frac{1}{|\mathcal{B}_1||\mathcal{B}_2|} \sum_v P_{U|V}(v|\Phi_c(s_0,b_1)) P_{Z|V}(z|v)^{\frac{1}{1-\rho}})^{1-\rho} \\
= & \mathrm{E}_{\Phi_c} \sum_z (\sum_{b_1} \frac{1}{|\mathcal{B}_1|} \sum_v P_{U|V}(v|\Phi_c(s_0,b_1)) P_{Z|V}(z|v)^{\frac{1}{1-\rho}})^{1-\rho} \\
\le & \sum_z \sum_{b_1} \mathrm{E}_{\Phi_c} (\frac{1}{|\mathcal{B}_1|} \sum_v P_{U|V}(v|\Phi_c(s_0,b_1)) P_{Z|V}(z|v)^{\frac{1}{1-\rho}})^{1-\rho} && (55) \\
= & \sum_z \sum_{b_1} \sum_u P_U(u) (\frac{1}{|\mathcal{B}_1|} \sum_v P_{U|V}(v|u) P_{Z|V}(z|v)^{\frac{1}{1-\rho}})^{1-\rho} \\
= & |\mathcal{B}_1|^\rho \sum_z \sum_u P_U(u) (\sum_v P_{U|V}(v|u) P_{Z|V}(z|v)^{\frac{1}{1-\rho}})^{1-\rho} \\
= & |\mathcal{B}_1|^\rho e^{\phi(\rho, P_{Z|V}, P_{V|U}, P_U)}, && (56)
\end{aligned}$$

where (53), (54), and (55) follow from (34), the concavity of $x \mapsto x^{1-\rho}$, and the inequality $(x+y)^{1-\rho} \le x^{1-\rho} + y^{1-\rho}$, respectively. Summarizing the above discussion, we obtain

$$
\begin{aligned}
& \mathrm{E}_{\tilde{\Phi}_a} e^{\rho I(S_{\mathcal{I}}:Z|S_0)[P_{Z|V},\tilde{\Phi}_a]} \\
\le & \mathrm{E}_{\tilde{\Phi}_a} \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) e^{\rho D(P_{Z|B_1,B_2,S_0=s_0,\Phi_a} \| \tilde{P}_{Z|S_0=s_0,\Phi_a})} \tag{57} \\
= & \mathrm{E}_{\Phi_a} \mathrm{E}_{F',G'|\Phi_a} \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) \\
& \qquad \cdot e^{\rho D(P_{Z|B_1,B_2,S_0=s_0,\Phi_a} \| \tilde{P}_{Z|S_0=s_0,\Phi_a})} \\
\le & \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) \\
& \cdot \mathrm{E}_{\Phi_a}(1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0)} e^{\psi(\rho,P_{Z|B_1,B_2,S_0,\Phi_a},P_{B_1,B_2})}) \tag{58} \\
\le & \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) \\
& \cdot (1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0)} |\mathcal{B}_1|^{\rho} e^{\phi(\rho,P_{Z|V},P_{V|U},P_U)}) \tag{59} \\
= & 1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}},S_0)} |\mathcal{B}_1|^{\rho} e^{\phi(\rho,P_{Z|V},P_{V|U},P_U)},
\end{aligned}
$$

where (57), (58), and (59) follow from (38), Lemma 15, and (56), respectively.

Further, (46) follows from Gallager bound. (45) can be shown similar to (16). ■

C. Second construction

Now, we introduce the second kind of random coding for SMC.

Construction 2: For a given Markov chain $U \to V \to X \to YZ$, we define the following random coding. For any element $s_0 \in \mathcal{S}_0$, $\Phi_c(s_0)$ is the random variable taking values in $\mathcal{U}$, is subject to the distribution P_U, and is independent of $\Phi_c(s_0')$ with $s_0' \neq s_0 \in \mathcal{S}_0$. For any element $(s_1, \ldots, s_T) \in \mathcal{S}_1 \times \cdots \times \mathcal{S}_T$, $\Phi_p(s_0, s_1, \ldots, s_T)$ is the random variable taking values in $\mathcal{V}$, is subject to the distribution $P_{V|U=\Phi_c(s_0)}$, and is independent of $\Phi_p(s_0', s_1', \ldots, s_T')$ with $(s_0', s_1', \ldots, s_T') \neq (s_0, s_1, \ldots, s_T)$. Similar to the above construction, Bob's decoder Φ_b and Eve's decoder Φ_e are defined as the maximum likelihood decoders. Hence, our code is written by the quartet $(\Phi_c, \Phi_p, \Phi_b, \Phi_e)$.

The averaged performance of the above code is evaluated by the following theorem. Indeed, we cannot derive the capacity region from the following theorem. For the strong security, we focus on the exponential decreasing rate of the conditional mutual information. As is explained in Section VII, the following theorem yields a better bound for this exponential decreasing rate than Theorem 16 in a specific case.

Theorem 17: The above ensemble of codes $\Phi = (\Phi_c, \Phi_p, \Phi_b, \Phi_e)$ satisfies the following inequalities.

$$
\begin{aligned}
& \mathrm{E}_{\Phi} \exp(\rho I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \Phi]) \\
\le & 1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}},S_0)+\psi(\rho,P_{Z|V},P_{V|U},P_U)}, \tag{60} \\
& \mathrm{E}_{\Phi} P_b[P_{Y|V}, \Phi] \\
\le & |\mathcal{S}|^{\rho} e^{\phi(-\rho,P_{Y|V},P_{V|U},P_U)} + (|\mathcal{S}_0||\mathcal{S}|)^{\rho} e^{\phi(-\rho,P_{Y|U,V},P_{U,V})}, \tag{61} \\
& \mathrm{E}_{\Phi} P_e[P_{Z|V}, \Phi] \le |\mathcal{S}_0|^{\rho} e^{\phi(-\rho,P_{Z|U},P_U)}. \tag{62}
\end{aligned}
$$

Applying Jensen's inequality to the convex function $x \mapsto e^x$, we obtain

$$
\begin{aligned}
& \mathrm{E}_{\Phi} \rho I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \Phi] \\
\le & \log(1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}},S_0)+\psi(\rho,P_{Z|V},P_{V|U},P_U)}) \\
\le & e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}},S_0)+\psi(\rho,P_{Z|V},P_{V|U},P_U)}. \tag{63}
\end{aligned}
$$

Markov inequality guarantees that there exists a code Φ such that

$$
\begin{aligned}
& \exp(\rho I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \Phi]) \\
\le & 2^{T+2}(1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}},S_0)+\psi(\rho,P_{Z|V},P_{V|U},P_U)}) \\
\le & 2^{T+3} e^{[-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}},S_0)+\psi(\rho,P_{Z|V},P_{V|U},P_U)]_+}, \tag{64} \\
& \rho I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \Phi] \\
\le & 2^{T+2} e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}},S_0)+\psi(\rho,P_{Z|V},P_{V|U},P_U)}, \tag{65} \\
& P_b[P_{Y|V}, \Phi] \\
\le & 2^{T+2}|\mathcal{S}|^{\rho} e^{\phi(-\rho,P_{Y|V},P_{V|U},P_U)} + 2^{T+2}|\mathcal{S}_0|^{\rho} e^{\phi(-\rho,P_{Y|U},P_U)}, \tag{66} \\
& P_e[P_{Z|V}, \Phi] \\
\le & 2^{T+2}|\mathcal{S}_0|^{\rho} e^{\phi(-\rho,P_{Z|U},P_U)}. \tag{67}
\end{aligned}
$$

Taking the logarithm in (64), we obtain

$$
\begin{aligned}
& I(S_{\mathcal{I}} : Z|S_0)[P_{Z|V}, \Phi] \\
\le & (T+3)\frac{\log 2}{\rho} + [\frac{1}{\rho}\psi(\rho, P_{Z|V}, P_{V|U}, P_U) - H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}, S_0)]_+. \tag{68}
\end{aligned}
$$

Proof of Theorem 17:

Inequalities (61) and (62) can be shown by Lemma 9. Then, we show (60).

Then, applying (39) to the case with $\tilde{P}_Z = P_{Z|U=\Phi_c(s_0)}$, we obtain

$$
\begin{aligned}
& \mathrm{E}_{\Phi} e^{\rho I(S_{\mathcal{I}}:Z|S_0,\Phi)} \\
\le & \mathrm{E}_{\Phi} \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) e^{\psi(\rho|P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi} \| P_{Z|U=\Phi_c(s_0)})} \\
= & \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) \\
& \cdot \mathrm{E}_{\Phi_c} \mathrm{E}_{\Phi_p|\Phi_c} e^{\psi(\rho|P_{Z|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0,\Phi} \| P_{Z|U=\Phi_c(s_0)})} \\
\le & \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) \\
& \cdot \mathrm{E}_{\Phi_c}(1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0)} e^{\psi(\rho,P_{Z|V},P_{V|U=\Phi_c(s_0)})}) \\
= & \sum_{s_0} P_{S_0}(s_0) \sum_{s_{\mathcal{I}}} P_{S_{\mathcal{I}}|S_0}(s_{\mathcal{I}}|s_0) \\
& \cdot (1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}}=s_{\mathcal{I}},S_0=s_0)} e^{\psi(\rho,P_{Z|V},P_{V|U},P_U)}) \\
= & 1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}},S_0)} e^{\psi(\rho,P_{Z|V},P_{V|U},P_U)},
\end{aligned}
$$

which implies (60). ■

VI. SECURE MULTIPLEX CODING WITH A COMMON MESSAGE: ASYMPTOTIC PERFORMANCE

In this section, we treat the asymptotic asymptotic performance for secure multiplex coding with a common message. First, we treat what performance can be achieved by using Theorem 16 in Subsection V-B without any assumption for the distribution of sources. In the next step, we define the capacity region under the asymptotic uniformity for information sources. In SMC, this restriction for the sources is essential for definition of the capacity region. After this definition, we concretely give the capacity region.

A. General case

In order to treat asymptotic analysis, for a given set of rates $(R_i)_{i=0}^T$, we introduce other parameters $R_{\rm p}$ and $R_{\rm c}$ satisfying

$$R_{\rm c} + R_{\rm p} = \sum_{i=0}^{T} R_i, \quad R_{\rm c} \geq R_0. \tag{69}$$

In the following, we denote the set of $((R_i)_{i=0}^T, R_{\rm p}, R_{\rm c})$ satisfying the above condition by $\mathcal{R}_T$. We choose the code Φ_n satisfying (48), (49), (50), and (51) in the length n case with $|\mathcal{S}_{i,n}| := e^{nR_i}$ for $i = 0, 1, \ldots, T$, $|\mathcal{B}_1| := e^{n(R_{\rm c}-R_0)}$, $|\mathcal{B}_2| := e^{nR_{\rm p}}$. Then, (50) and (51) guarantee that

$$\lim_{n\to\infty} \frac{-1}{n} \log P_b[P^n_{Y|V}, \Phi_n] \geq \tilde{E}^{\rm Y}(R_{\rm p}, R_{\rm c}, P_{Y,V,U}), \tag{70}$$

$$\lim_{n\to\infty} \frac{-1}{n} \log P_e[P^n_{Z|V}, \Phi_n] \geq \tilde{E}^{\rm Z}(R_{\rm c}, P_{Z,U}),. \tag{71}$$

When

$$R_{\rm c} < \min[I(Y:U), I(Z:U)], \quad R_{\rm p} < I(Y:V|U), \tag{72}$$

the above both exponents are positive, i.e., the both error probabilities go to zero exponentially. Further, due to (52), the leaked information for $S_{\mathcal{I},n}$ can be evaluated as

$$\begin{aligned} &\frac{1}{n} I(S_{\mathcal{I},n} : Z^n | S_{0,n})[P^n_{Z|V}, \Phi_{a,n}] \\ \leq& \Big[[R_{\rm c} - R_0]_+ + \frac{1}{\rho}\phi(\rho, P_{Z|V}, P_{V|U}, P_U) - \frac{1}{n} H_{1+\rho}(S_{\mathcal{I}^c,n} | S_{\mathcal{I},n}, S_{0,n}) \Big]_+ \\ &+ (T+3)\frac{\log 2}{n\rho} \end{aligned}$$

Substituting $\rho = a/n$ and taking the limits $n \to \infty$, we obtain

$$\begin{aligned} &\limsup_{n\to\infty} \frac{1}{n} I(S_{\mathcal{I},n} : Z_n | S_{0,n})[P^n_{Z|V}, \Phi_{a,n}] \qquad (73) \\ \leq& \Big[(R_{\rm c} - R_0) + I(Z:V|U) - \liminf_{n\to\infty} \frac{1}{n} H_{1+a/n}(S_{\mathcal{I}^c,n} | S_{\mathcal{I},n}, S_{0,n}) \Big]_+ \\ &+ (T+3)\frac{\log 2}{a} \end{aligned}$$

Taking the limits $a \to \infty$, we obtain

$$\begin{aligned} &\limsup_{n\to\infty} \frac{1}{n} I(S_{\mathcal{I},n} : Z_n | S_{0,n})[P^n_{Z|V}, \Phi_{a,n}] \qquad (74) \\ \leq& \Big[(R_{\rm c} - R_0) + I(Z:V|U) \\ &- \lim_{a\to\infty} \liminf_{n\to\infty} \frac{1}{n} H_{1+a/n}(S_{\mathcal{I}^c,n} | S_{\mathcal{I},n}, S_{0,n}) \Big]_+ . \qquad (75) \end{aligned}$$

So, the asymptotic performance of our code is characterized in (70), (71), and (75).

B. Capacity region

In SMC, we use the message $S_{\mathcal{I}^c}$ as a dummy message. The secrecy of the message $S_{\mathcal{I}}$ depends on the entropy of the dummy message $S_{\mathcal{I}^c}$. Then, we cannot define the capacity region without fixing the entropy rate of the dummy message $S_{\mathcal{I}^c}$. In order to resolve this problem, we introduce the asymptotic uniformity condition. When the sequence of the dummy message $S_{\mathcal{I}^c,n}$ satisfies

$$\lim_{n\to\infty} \frac{1}{n} H(S_{\mathcal{I}^c,n} | S_{\mathcal{I},n}, S_{0,n}) = \sum_{i\in\mathcal{I}^c} R_i, \tag{76}$$

it is called asymptotically uniform. In fact, as is shown as Folklore source coding theorem[9], when the original message is compressed up to the entropy rate, the condition (76) holds. Even if the dummy message $S_{\mathcal{I}^c,n}$ satisfies the condition (76), it is not necessarily uniform or independent of $S_{\mathcal{I},n}$ or $S_{0,n}$.

In order to characterize the limit of the asymptotic performance of secure multiplex coding with a common message, we give the capacity region in the following way.

Definition 18: The rate tuple $(R_0, R_1, \ldots, R_T)$ and the equivocation rate tuple $\{R_{l,\mathcal{I}} \mid \emptyset \neq \mathcal{I} \subseteq \{1, \ldots, T\}\}$ are said to be *achievable* for the secure multiplex coding with T secret messages if the following conditions hold. When a sequence of joint distribution for all of the i-th secret $S_{i,n}$ on $\mathcal{S}_{i,n}$ with cardinality e^{nR_i} and the common message $S_{0,n}$ on $\mathcal{S}_{0,n}$ with cardinality e^{nR_0} satisfies (76) for $i = 1, \ldots, T$, there exist a sequence of codes $\varphi_n = (\varphi_{a,n}, \varphi_{b,n}, \varphi_{e,n})$, i.e., Alice's stochastic encoder $\varphi_{a,n}$ from $\mathcal{S}_{0,n} \times \mathcal{S}_{1,n} \times \cdots \times \mathcal{S}_{T,n}$ to $\mathcal{X}^n$, Bob's deterministic decoder $\varphi_{b,n} : \mathcal{Y}^n \to \mathcal{S}_{0,n} \times \mathcal{S}_{1,n} \times \cdots \times \mathcal{S}_{T,n}$ and Eve's deterministic decoder $\varphi_{e,n} : \mathcal{Z}^n \to \mathcal{S}_{0,n}$ such that

$$\begin{aligned} \lim_{n\to\infty} P_b[P^n_{Y|X}, \varphi_n] &= 0 \\ \lim_{n\to\infty} P_e[P^n_{Z|X}, \varphi_n] &= 0 \\ \limsup_{n\to\infty} I(S_{\mathcal{I},n} : Z^n | S_0)[P^n_{Z|X}, \varphi_{a,n}] &\leq R_{l,\mathcal{I}} \end{aligned}$$

where $S_{\mathcal{I},n}$ is the collection of random variables $S_{i,n}$ with $i \in \mathcal{I}$, and Y^n and Z^n are the received signal by Bob and Eve, respectively, with the transmitted signal $f_n(S_{1,n}, \ldots, S_{T,n}, E_n)$ and the channel transition probabilities $P_{Y|X}$, $P_{Z|X}$.

The capacity region of the secure multiplex coding is the closure of the achievable rate tuples.

Theorem 19: The capacity region for the secure multiplex coding with a common message is given by the set of R_0, R_1, $\ldots$, R_T and $\{R_{l,\mathcal{I}} \mid \emptyset \neq \mathcal{I} \subseteq \{1, \ldots, T\}\}$ such that there exist a Markov chain $U \to V \to X \to YZ$ and

$$\begin{aligned} R_0 &\leq \min[I(U;Y), I(U;Z)], \\ \sum_{i=0}^{T} R_i &\leq I(V;Y|U) + \min[I(U;Y), I(U;Z)] \\ R_{l,\mathcal{I}} &\geq [\sum_{i\in\mathcal{I}} R_i + I(Z:V|U) - I(Y:V|U)]_+ \qquad (77) \end{aligned}$$

for all $\emptyset \neq \mathcal{I} \subseteq \{1, \ldots, T\}$.

Proof. The converse part of this coding theorem follows from that for Theorem 2 with the uniform distribution on the total message sets. We have to show the direct part. Choose a sufficient small real number $\epsilon > 0$ and $(R_i)_{i=0}^T$ for $i = 0, 1, \ldots, T$ satisfying

$$\begin{aligned} R_0 &< \min[I(U;Y), I(U;Z)], \qquad (78) \\ (\sum_{i=0}^{T} R_i) + \epsilon &< I(V;Y|U) + \min[I(U;Y), I(U;Z)]. \qquad (79) \end{aligned}$$

Assume that the sequence of the joint distribution of information source satisfies (76). Then, it is sufficient to show the existence of a sequence of codes $\{\Phi_n\}$ such that

$$\lim_{n\to\infty} P_b[P^n_{Y|V}, \Phi_n] = 0 \tag{80}$$

$$\lim_{n\to\infty} P_e[P^n_{Z|V}, \Phi_n] = 0 \tag{81}$$

and

$$\begin{aligned}&\limsup_{n\to\infty} \frac{1}{n} I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n]\\ \le&[\sum_{i\in\mathcal{I}} R_i + I(Z : V|U) - I(Y : V|U) + \epsilon]_+.\end{aligned} \tag{82}$$

Based on the choices $R_{\rm p} := I(Y : V|U) - \epsilon$ and $R_{\rm c} := \sum_{i=0}^T R_i - R_{\rm p}$, we construct the code Φ_n in the above way. Since the conditions (78) and (79) guarantee the conditions (72), we obtain (80) and (81). The condition (76) and Lemma 26 guarantees

$$\lim_{a\to\infty}\liminf_{n\to\infty} \frac{1}{n} H_{1+a/n}(S_{\mathcal{I}^c,n}|S_{\mathcal{I},n}, S_{0,n}) = \sum_{i\in\mathcal{I}^c} R_i. \tag{83}$$

(75) and (83) yields

$$\begin{aligned}&\limsup_{n\to\infty} \frac{1}{n} I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_{a,n}]\\ \le&[(R_{\rm c} - R_0) + I(Z : V|U) - \sum_{i\in\mathcal{I}^c} R_i]_+\\ =&[R_{\rm c} - \sum_{i=0}^T R_i + I(Z : V|U) + \sum_{i\in\mathcal{I}} R_i]_+\\ =&[-R_{\rm p} + I(Z : V|U) + \sum_{i\in\mathcal{I}} R_i]_+..\end{aligned} \tag{84}$$

Therefore, since $R_{\rm p} = I(Y : V|U) - \epsilon$, (84) implies (82). ■

VII. Secure multiplex coding with a common message: strong security

In this section, we show the strong security for secure multiplex coding with a common message.

When conditions (78) and (79) holds and

$$\begin{aligned}&\lim_{\rho\to 0}\liminf_{n\to\infty} \frac{1}{n} H_{1+\rho}(S_{\mathcal{I}^c,n}|S_{\mathcal{I},n}, S_{0,n})\\ >&\sum_{i=1}^T R_i - I(Y : V|U) + I(Z : V|U),\end{aligned} \tag{85}$$

we can show that the above code satisfies

$$\lim_{n\to\infty} I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n] = 0. \tag{86}$$

This property is called strong security. Then, we choose $R_{\rm p}$ to be $I(Y : V|U) - \min[\frac{\text{LHS–RHS in (85)}}{2}, \epsilon]$, which guarantees (80) and (81). Due to (49), the leaked information for $S_{\mathcal{I},n}$ can be evaluated as

$$\begin{aligned}&I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n]\\ \le&\frac{2^{T+2}}{\rho} e^{\rho n(R_{\rm c}-R_0)-\rho H_{1+\rho}(S_{\mathcal{I}^c,n}|S_{\mathcal{I},n},S_{0,n})+n\phi(\rho,P_{Z|V},P_{V|U},P_U)}.\end{aligned}$$

We obtain

$$\begin{aligned}&\lim_{n\to\infty} \frac{-1}{n} \log I(S_{\mathcal{I},n} : Z_n|S_{0,n})\\ \ge&\rho \lim_{n\to\infty} \frac{1}{n} H_{1+\rho}(S_{\mathcal{I}^c,n}|S_{\mathcal{I},n}, S_{0,n})\\ &- \rho(R_{\rm c} - R_0) - \phi(\rho, P_{Z|V}, P_{V|U}, P_U).\end{aligned} \tag{87}$$

Therefore,

$$\begin{aligned}&\lim_{\rho\to 0} \frac{1}{\rho}\Big(\rho \lim_{n\to\infty} \frac{1}{n} H_{1+\rho}(S_{\mathcal{I}^c,n}|S_{\mathcal{I},n}, S_{0,n})\\ &\qquad - \rho(R_{\rm c} - R_0) - \phi(\rho, P_{Z|V}, P_{V|U}, P_U)\Big)\\ =&\lim_{\rho\to 0}\liminf_{n\to\infty} \frac{1}{n} H_{1+\rho}(S_{\mathcal{I}^c,n}|S_{\mathcal{I},n}, S_{0,n}) - \sum_{i=1}^T R_i + R_{\rm p} - I(Z : V|U)\\ \ge&\frac{1}{2}\Big(\lim_{\rho\to 0}\liminf_{n\to\infty} \frac{1}{n} H_{1+\rho}(S_{\mathcal{I}^c,n}|S_{\mathcal{I},n}, S_{0,n})\\ &\qquad - \sum_{i=1}^T R_i + I(Y : V|U) - I(Z : V|U)\Big)\\ >&0.\end{aligned} \tag{88}$$

Hence, RHS of (87) is strictly positive with small $\rho > 0$. Thus, we obtain (86).

When we assume a stronger condition:

$$\lim_{n\to\infty} \frac{1}{n} H_{1+\rho}(S_{\mathcal{I}^c,n}|S_{\mathcal{I},n}, S_{0,n}) = \sum_{i\in\mathcal{I}^c} R_i \tag{89}$$

for $\rho \in (0, 1]$, using (87), we obtain

$$\begin{aligned}&\lim_{n\to\infty} \frac{-1}{n} \log I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n]\\ \ge&\rho(R_{\rm p} - \sum_{i\in\mathcal{I}} R_i) - \phi(\rho, P_{Z|V}, P_{V|U}, P_U).\end{aligned}$$

Hence, we obtain the following theorem.

Theorem 20: Assume that the condition (89) holds. For given $(R_i)_{i=0}^T$, we choose $R_{\rm p}$ and $R_{\rm c}$ as follows.

$$R_{\rm c} > R_0, \quad R_{\rm c} + R_{\rm p} = \sum_{i=0}^T R_i.$$

Then, there exists a sequence of codes Φ_n such that

$$\lim_{n\to\infty} \frac{-1}{n} \log P_b[P^n_{Y|V}, \Phi_n] \ge \tilde{E}^b(R_{\rm p}, R_{\rm c}, P_{Y,V,U}), \tag{90}$$

$$\lim_{n\to\infty} \frac{-1}{n} \log P_e[P^n_{Z|V}, \Phi_n] \ge \tilde{E}^e(R_{\rm c}, P_{Z,U}). \tag{91}$$

$$\lim_{n\to\infty} \frac{-1}{n} \log I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n] \ge \tilde{E}^\phi(R_{\rm p} - \sum_{i\in\mathcal{I}} R_i, P_{Z,V,U}), \tag{92}$$

where the functions $\tilde{E}^b$, $\tilde{E}^e$, and $\tilde{E}^\phi$ are given in (8)-(10). When $R_{\rm p} - \sum_{i\in\mathcal{I}} R_i > I(Z : V|U)$, the above exponent is positive, i.e., the leaked information goes to zero exponentially. In particular, when

$$\sum_{i=1}^T R_i < I(Y : V|U), \; R_0 < \min[I(U; Y), I(U; Z)], \tag{93}$$

we can choose R_{p} and R_{c} by $R_{\mathrm{p}} := \sum_{i=1}^{T} R_i$ and $R_{\mathrm{c}} := R_0$. Then, the above inequalities can be simplified to

$$\lim_{n\to\infty} \frac{-1}{n} \log P_b[P^n_{Y|V}, \Phi_n] \ge \tilde{E}^b(\sum_{i=1}^{T} R_i, R_0, P_{Y,V,U}), \tag{94}$$

$$\lim_{n\to\infty} \frac{-1}{n} \log P_e[P^n_{Z|V}, \Phi_n] \ge \tilde{E}^e(R_0, P_{Z,U}). \tag{95}$$

$$\lim_{n\to\infty} \frac{-1}{n} \log I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n] \ge \tilde{E}^\phi(\sum_{i\in\mathcal{I}^c} R_i, P_{Z,V,U}). \tag{96}$$

The exponent (96) can be improved by using Theorem 17 when the condition (93) holds. In this case, we choose the code Φ_n satisfying (64), (65), (66), and (67) in the length n case with $|\mathcal{S}_{i,n}| := e^{nR_i}$ for $i = 0, 1, \ldots, T$. In the code Φ_n, the exponential decreasing rate of error probabilities are evaluated in the same way as (94) and (95). Similarly, using (68), we can show that

$$\begin{aligned}
&\limsup_{n\to\infty} \frac{1}{n} I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n] \\
\le&[I(Z : V|U) - \sum_{i\in\mathcal{I}^c} R_i]_+ \\
=&[I(Z : V|U) - I(Y : V|U) + \sum_{i\in\mathcal{I}} R_i]_+
\end{aligned} \tag{97}$$

because $\lim_{\rho\to 0} \frac{1}{\rho}\psi(\rho, P_{Z|V}, P_{V|U}, P_U) = I(Z : V|U)$. From (65), in the case (93), we have

$$I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n] \le \frac{2^{T+2}}{\rho} e^{n(-\rho \sum_{i\in\mathcal{I}^c} R_i + \psi(\rho, P_{Z|V}, P_{V|U}, P_U))}.$$

Then,

$$\begin{aligned}
&\lim_{n\to\infty} \frac{-1}{n} \log I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n] \\
\ge&\rho \sum_{i\in\mathcal{I}^c} R_i - \phi(\rho, P_{Z|V}, P_{V|U}, P_U).
\end{aligned}$$

Hence, we obtain the following theorem.

Theorem 21: Under the same condition as Theorem 20, there exists a sequence of codes Φ_n satisfying (94), (95), and

$$\lim_{n\to\infty} \frac{-1}{n} \log I(S_{\mathcal{I},n} : Z_n|S_{0,n})[P^n_{Z|V}, \Phi_n] \ge \tilde{E}^\psi(\sum_{i\in\mathcal{I}^c} R_i, P_{Z,V,U}), \tag{98}$$

where

$$\tilde{E}^\psi(R, P_{Z,V,U}) := \max_{0\le\rho\le 1} \rho R - \psi(\rho, P_{Z|V}, P_{V|U}, P_U).$$

Due to (34), (98) is better than (96) when (93). However, (92) is more general than (98).

VIII. PRACTICAL CODE CONSTRUCTION

In Section VIII, we consider how we can construct practically usable encoder and decoder for the secure multiplex coding. We shall show that how to convert an ordinary error correcting code without secrecy consideration to a code for the secure multiplex coding.

A. First Practical Construction

We consider to attach F' and G' in Lemma 15 to an arbitrary given error-correcting code in order to obtain a code for secure multiplex coding. To use the code with F' and G' attached, we have to evaluate the amount of information leaked to Eve. Theorem 16 provides the average amount of leaked information averaged over the ensemble of the error correcting code $\Phi_a = (\Phi_{\mathrm{c}}, \Phi_{\mathrm{p}})$ while Lemma 15 gives the average amount for a fixed error correcting code $\Phi_a = (\Phi_{\mathrm{c}}, \Phi_{\mathrm{p}})$. However, the RHS of (40) is too complicated to be computable in practice. A computable upper bound is given as follows.

$$\begin{aligned}
&e^{\psi(\rho, P_{Z|B_1,B_2,\Phi_a,S_0}, \bar{P}_{B_1,B_2})} \le e^{\phi(\rho, P_{Z|B_1,B_2,\Phi_a,S_0}, \bar{P}_{B_1,B_2})} \\
=& \sum_z (\sum_{b_1,b_2} \frac{1}{|\mathcal{B}_1||\mathcal{B}_2|} P_{Z|V}(z|\Phi_{\mathrm{p}}(s_0, b_1, b_2))^{\frac{1}{1-\rho}})^{1-\rho} \\
\le& \max_{P_V} \sum_z (\sum_v P_V(v) P_{Z|V}(z|v)^{\frac{1}{1-\rho}})^{1-\rho}.
\end{aligned}$$

When $P_{Z|V}(z|v)$ is n-fold memoryless extension, by [1]

$$\max_{P_{V^n}} \sum_z (\sum_v P_{V^n}(v) P_{Z^n|V^n}(z|v)^{\frac{1}{1-\rho}})^{1-\rho} = e^{n\phi_{\max}(\rho, P_{Z|V})},$$

where

$$\phi_{\max}(\rho, P_{Z|V}) := \log \max_{P_V} \sum_z (\sum_v P_V(v) P_{Z|V}(z|v)^{\frac{1}{1-\rho}})^{1-\rho}. \tag{99}$$

Observe that RHS of (99) can be easily computed by the standard convex optimization because $\sum_z(\sum_v P_V(v) P_{Z|V}(z|v)^{\frac{1}{1-\rho}})^{1-\rho}$ is a convex function of P_V with fixed ρ [7]. Then, we obtain an upper bound:

$$\mathrm{E}_{F',G'|\Phi_a} e^{\rho I(S_{\mathcal{I}}:Z|S_0)[P^n_{Z|V},(\Phi_a,\Lambda_{F',G'})])} \le 1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}},S_0)} e^{n\phi(\rho, P_{Z|V})} \tag{100}$$

Suppose that we are given arbitrary error-correcting code Φ_a for the memoryless channel $P_{YZ|V}$. The code Φ_a can be, for example, an LDPC code or a Turbo code. By using Eq. (100), from Φ_a we can construct a code for secure multiplex coding as follows:

1) For each nonemptyset $\mathcal{I} \subseteq \{1, \ldots, T\}$, fix maximum acceptable information leakage $\epsilon_{\mathcal{I}}$ for $I(S_{\mathcal{I}} : Z|S_0)$.
2) Fix maximum acceptable probability ϵ_2 for a chosen F', G' not making $I(S_{\mathcal{I}} : Z|S_0)$ below $\epsilon_{\mathcal{I}}$.
3) By using (100) compute information rate for each secret message S_i so that

$$\mathrm{E}_{F',G'|\Phi_a} I(S_{\mathcal{I}} : Z|S_0)[P^n_{Z|V}, (\Phi_a, \Lambda_{F',G'})] \le \epsilon_2 \epsilon_{\mathcal{I}}/2^T$$

for every $\mathcal{I}$.
4) Then the probability of choosing F' and G' making $I(S_{\mathcal{I}} : Z|S_0) \le \epsilon_{\mathcal{I}}$ is $\ge 1 - \epsilon_2$.

Further, the value $\phi_{\max}(\rho, P_{Z|V})$ can be calculated in the regular case as follows.

Lemma 22: When the channel $P_{Z|V}$ is regular in the sense of Delsarte-Piret [6],

$$\phi_{\max}(\rho, P_{Z|V}) = \phi(\rho, P_{Z|V}, P_{V,\mathrm{mix}}), \tag{101}$$

where $P_{V,\mathrm{mix}}$ is the uniform distribution on $\mathcal{V}$.

Proof: First, we choose P'_V such that

$$\phi_{\max}(\rho, P_{Z|V}) = \phi(\rho, P_{Z|V}, P'_V).$$

Define P'_{V,v_0} for $v_0 \in \mathcal{V}$ by

$$P'_{V,v_0}(v) = P'_V(v + v_0).$$

Then,

$$e^{\phi(\rho,P_{Z|V},P'_V)} = e^{\phi(\rho,P_{Z|V},P'_{V,v_0})}.$$

The concavity $P_V \mapsto e^{\phi(\rho,P_{Z|V},P_V)}$ implies that

$$\sum_{v_0\in\mathcal{V}} \frac{1}{|\mathcal{V}|} e^{\phi(\rho,P_{Z|V},P'_{V,v_0})} \le e^{\phi(\rho,P_{Z|V},\sum_{v_0\in\mathcal{V}} \frac{1}{|\mathcal{V}|} P'_{V,v_0})} = e^{\phi(\rho,P_{Z|V},P_{V,\mathrm{mix}})},$$

which implies (101). ■

B. Second Practical Construction

Now, we consider the case when there is no common message and a code $\Phi_{\mathrm{p}} : \mathcal{B}_2 \to \mathcal{V}$ is given. In the following, we assume that a module structure in V and the map Φ_{p} is a homomorphism. However, we do not necessarily assume any algebraic structure in the channel $P_{Z,Y|V}$, now. Then, we modify the random code given in Lemma as follows. We choose an ensemble of isomorphisms F' from $\mathcal{S}_1 \times \cdots \times \mathcal{S}_T$ to $\mathcal{B}_2$ satisfying Condition 11. We choose the random variable $G'' \in \mathcal{V}$ that obeys the uniform distribution on $\mathcal{V}$ that is independent of the choice of F'. When Φ_{p} is a linear code such as an LDPC code or a Turbo code, G'' means that we are using the set of codewords having a common nonzero syndrome, while the ordinary linear code consists of codewords having the zero syndrome. Then, we define a map $\Lambda_{F',G''}(s) := \Phi_{\mathrm{p}} \circ F'(s) + G''$ and have the following lemma:

Lemma 23:

$$\mathrm{E}_{F',G''|\Phi_{\mathrm{p}}} e^{\rho I(S_{\mathcal{I}}:Z)[P^n_{Z|V},(\Phi_{\mathrm{p}},\Lambda_{F',G''})])} \le 1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}})} e^{\phi(\rho,P_{Z|V},P_{V,\mathrm{mix}})}.$$

Thus, in the n-fold memoryless extension case, we have

$$\mathrm{E}_{F',G''|\Phi_{\mathrm{p}}} e^{\rho I(S_{\mathcal{I}}:Z)[P^n_{Z|V},(\Phi_{\mathrm{p}},\Lambda_{F',G'})]} \le 1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}})} e^{n\phi(\rho,P_{Z|V},P_{V,\mathrm{mix}})}. \tag{102}$$

Proof: Now, we define the random variable $H \in \mathcal{V}/\Phi_{\mathrm{p}}(\mathcal{B}_2)$ that obeys the uniform distribution. Let $\{y_h\}$ be the set of coset representatives. Let G' be the random variable subject to the uniform distribution on $\mathcal{B}_1$. Then, G'' is given as $\Phi_{\mathrm{p}}(G') + y_H$.

$$\begin{aligned}
&\mathrm{E}_{F',G''|\Phi_{\mathrm{p}}} e^{\rho I(S_{\mathcal{I}}:Z)[P^n_{Z|V},(\Phi_{\mathrm{p}},\Lambda_{F',G''})]} \\
=&1 + \mathrm{E}_{H|\Phi_{\mathrm{p}}} \mathrm{E}_{F',G''|H,\Phi_{\mathrm{p}}} e^{\rho I(S_{\mathcal{I}}:Z)[P^n_{Z|V},(\Phi_{\mathrm{p}},\Lambda_{F',G''})]} \\
\le&1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}})} \mathrm{E}_{H|\Phi_{\mathrm{p}}} \sum_z (\sum_{b_2} \frac{1}{|\mathcal{B}_2|} P_{Z|V}(z|\Psi(b_2) + y_H)^{\frac{1}{1-\rho}})^{1-\rho} \\
\le&1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}})} \sum_z (\mathrm{E}_{H|\Phi_{\mathrm{p}}} \sum_{b_2} \frac{1}{|\mathcal{B}_2|} P_{Z|V}(z|\Phi_{\mathrm{p}}(b_2) + y_H)^{\frac{1}{1-\rho}})^{1-\rho} \\
=&1 + e^{-\rho H_{1+\rho}(S_{\mathcal{I}^c}|S_{\mathcal{I}})} e^{\phi(\rho,P_{Z|V},P_{V,\mathrm{mix}})}.
\end{aligned}$$

■

Suppose that we are given arbitrary error-correcting code Φ_{p} for the memoryless channel $P_{Y|V}$. By using Eq. (102), from Φ_{p} we can construct a code for secure multiplex coding (with no common message) as follows:

1) For each nonemptyset $\mathcal{I} \subseteq \{1, \ldots, T\}$, fix maximum acceptable information leakage $\epsilon_{\mathcal{I}}$ for $I(S_{\mathcal{I}} : Z)$.
2) Fix maximum acceptable probability ϵ_2 for a chosen F', G'' not making $I(S_{\mathcal{I}} : Z)$ below $\epsilon_{\mathcal{I}}$.
3) By using (102) compute information rate for each secret message S_i so that

$$\mathrm{E}_{F',G''|\Phi_{\mathrm{p}}} I(S_{\mathcal{I}} : Z)[P^n_{Z|V}, (\Phi_{\mathrm{p}}, \Lambda_{F',G''})] \le \epsilon_2 \epsilon_{\mathcal{I}}/2^T$$

   for every $\mathcal{I}$.
4) Then the probability of choosing F' and G'' making $I(S_{\mathcal{I}} : Z|S_0) \le \epsilon_{\mathcal{I}}$ is $\ge 1 - \epsilon_2$.

IX. UNIVERSAL CODING FOR SECURE MULTIPLEX CODING WITH A COMMON MESSAGE

In order to treat universal coding for the multiplex coding with a common message,

We introduce the universally attainable exponents for the multiplex coding with a common message by adjusting the original definition for the BCD given by Körner and Sgarro [17].

Definition 24: Let $\mathcal{W}(\mathcal{X}, \mathcal{Y}, \mathcal{Z})$ be the set of all discrete memoryless broadcast channels $W : \mathcal{X} \to \mathcal{Y}, \mathcal{Z}$, and $\mathbf{R}^+$ the set of positive real numbers. A set of functions $(\tilde{E}^b, \tilde{E}^e, (\tilde{E}^{\mathcal{I}}_+, \tilde{E}^{\mathcal{I}}_-)_{\mathcal{I}\subset\{1,\ldots,T\}})$ from $\mathcal{R}_T \times \mathcal{W}(\mathcal{X}, \mathcal{Y}, \mathcal{Z})$ to $[\mathbf{R}^+ \cup \{0\}]^{2^{T+1}+2}$ is said to be a universally attainable quadruple of exponents and equivocation rate for the family $\mathcal{W}(\mathcal{X}, \mathcal{Y}, \mathcal{Z})$ if there exist a sufficiently small real number $\delta > 0$ and a sufficiently large integer N satisfying the following condition for $R_{\mathrm{p}} > 0$, $R_{\mathrm{c}} > 0$, $\epsilon > 0$, $(R_i)_{i=0,1,\ldots,T} \in (\mathbf{R}^+)^{T+1}$. When a sequence of joint distribution for all of the i-th secret $S_{i,n}$ on $\mathcal{S}_{i,n}$ with cardinality e^{nR_i} and the common message $S_{0,n}$ on $\mathcal{S}_{0,n}$ with cardinality e^{nR_0} satisfies

$$\frac{1}{n} H(S_{\mathcal{I}^c,n}|S_{\mathcal{I},n}, S_{0,n}) \ge \sum_{i\in\mathcal{I}^c} (R_i - \delta) \tag{103}$$

for $i = 1, \ldots, T$, $\rho \in (0, 1]$ and $n \ge N$, there exists a sequence of codes Φ_n of length n of rates at least $(R_i)_{i=0,1,\ldots,T}$ such that

$$P_b[W^n, \Phi_n] \le \exp(-n[\tilde{E}^b(R_{\mathrm{p}}, R_{\mathrm{c}}, (R_i)_{i=0,1,\ldots,T}, W) - \epsilon]), \tag{104}$$

$$P_e[W^n, \Phi_n] \le \exp(-n[\tilde{E}^e(R_{\mathrm{p}}, R_{\mathrm{c}}, (R_i)_{i=0,1,\ldots,T}, W) - \epsilon]), \tag{105}$$

and

$$\begin{aligned}
&I(S_{\mathcal{I},n} : Z_n|S_{0,n})[W^n, \Phi_n] \\
&\le \max\Big\{\exp(-n[\tilde{E}^{\mathcal{I}}_+(R_{\mathrm{p}}, R_{\mathrm{c}}, (R_i)_{i=0,1,\ldots,T}, W) - \epsilon]), \\
&\qquad n[\tilde{E}^{\mathcal{I}}_-(R_{\mathrm{p}}, R_{\mathrm{c}}, (R_i)_{i=0,1,\ldots,T}, W) + \epsilon]\Big\},
\end{aligned} \tag{106}$$

for the n-th memoryless extension of the channel $W \in \mathcal{W}(\mathcal{X}, \mathcal{Y}, \mathcal{Z})$ and $n \ge N$.

Suppose that we are given a broadcast $W : \mathcal{X} \to \mathcal{Y}, \mathcal{Z}$ and positive real numbers R_{p} and R_{c}. We fix a distribution Q_{UV} on $\mathcal{U} \times \mathcal{V}$, a channel $\Xi : \mathcal{V} \to \mathcal{X}$ and the rates $(R_{\mathrm{p}}, R_{\mathrm{c}}, (R_i)_{i=0,1,\ldots,T}) \in \mathcal{R}_T$, where the RVs U ,V, X, Y and Z are distributed according to Q_{UV}, Ξ and W. We present a universally attainable quadruple of exponents and leaked information rate in terms of R_p, R_c, Q_{UV} and Ξ as

$$\begin{aligned} E^b =&E^b(R_\mathrm{p}, R_\mathrm{c}, (R_i)_{i=0,1,\ldots,T}, W) \\ =&\tilde{E}^b(R_\mathrm{p}, R_\mathrm{c}, (W \circ \Xi) \cdot Q_{UV}), \end{aligned} \tag{107}$$

$$\begin{aligned} E^e =&E^e(R_\mathrm{p}, R_\mathrm{c}, (R_i)_{i=0,1,\ldots,T}, W) \\ =&\tilde{E}^e(R_\mathrm{c}, (W \circ \Xi) \cdot Q_{UV}), \end{aligned} \tag{108}$$

$$\begin{aligned} E^{\mathcal{I}}_+ =&E^{\mathcal{I}}_+(R_\mathrm{p}, R_\mathrm{c}, (R_i)_{i=0,1,\ldots,T}, W) \\ =&\tilde{E}^\phi(R_\mathrm{p} - \sum_{i\in\mathcal{I}} R_i, (W \circ \Xi) \cdot Q_{UV}), \end{aligned} \tag{109}$$

$$\begin{aligned} E^{\mathcal{I}}_- =&E^{\mathcal{I}}_-(R_\mathrm{p}, R_\mathrm{c}, (R_i)_{i=0,1,\ldots,T}, W) \\ =&I(V; Z|U) - R_\mathrm{p} + \sum_{i\in\mathcal{I}} R_i, \end{aligned} \tag{110}$$

which are given in (70), (71), (92), and (84).

Theorem 25 (Extension of [17, Theorem 1, part (a)]): Eqs. (107)–(110) are universally attainable rates of exponents and equivocation rate in the sense of Definition 24.

Proof. We shall attach our evaluation to the constant composition code used by Körner and Sgarro. We do not evaluate the decoding error probability, because that of our code is not larger than [17]. Observe that our exponents in Eqs. (107) and (108) are the same as [17] with the channel $W \circ \Xi$. We shall evaluate the mutual information.

We assume for a while that Q_{UV} is a type of a sequence of length n over $\mathcal{U} \times \mathcal{V}$. Recall that their codebook [17, Appendix] in the random coding is chosen according to the uniform distribution on the sequences with joint type Q_{UV}. We apply the random coding $\Phi_{a,n} = (\Phi_{c,n}, \Phi_{p,n})$ for message $S_{0,n}, B_{1,n}, B_{2,n}$ and the other random coding $\Lambda_{F,G,n}$ for message $S_{1,n}, \ldots, S_{T,n}$ given in Section V. That is, the encoder is given by $\tilde{\Phi}_{a,n} = (\Phi_{a,n}, \Lambda_{F,G,n})$. In the following, Bob's decoder $\Phi_{b,n}$ and Eve's decoder $\Phi_{e,n}$ are given as the maximum likelihood decoder. We treat the ensemble of codes $\Phi_n := (\tilde{\Phi}_{a,n}, \Phi_{b,n}, \Phi_{e,n})$.

Since we are using the constant composition code as used in [17], U^n and V^n are not i.i.d. RVs. So, the distribution P_{V^n,U^n} satisfies

$$P_{V^n|U^n=u}(v) \le (n+1)^{|\mathcal{U}\times\mathcal{V}|} Q^n_{V|U}(v|u) \tag{111}$$

for a fixed $u \in \mathcal{U}^n$ by [3, Lemma 2.5, Chapter 1], and

$$P_{U^n}(u) \le (n+1)^{|\mathcal{U}|} Q^n_U(u), \tag{112}$$

by [3, Lemma 2.3, Chapter 1].

In the following discussion, since we treat the channel $W^n_{\mathcal{Z}} \circ \Xi^n : \mathcal{V}^n \to \mathcal{Z}^n$, we simplify it to $\overline{W}^n_{\mathcal{Z}}$. Then, (35) yields that

$$\begin{aligned} &\exp(\phi(\rho, \overline{W}^n_{\mathcal{Z}}, P_{V^n|U^n}, P_{U^n})) \\ \le&(n+1)^{|\mathcal{U}|^2|\mathcal{V}|} \exp(\phi(\rho, \overline{W}^n_{\mathcal{Z}}, Q^n_{V|U}, Q^n_U)). \end{aligned} \tag{113}$$

In our code $\Phi_{a,n}$, the random variable V^n takes values in the subset $T_n(Q_V)$, which is defined as the set of elements of $\mathcal{V}^n$ whose type is Q_V. Hence, it is sufficient to treat the channel whose input system is the subset $T_n(Q_V)$ of $\mathcal{V}^n$. Then, we have the following convex combination:

$$\overline{W}^n_{\mathcal{Z}}|_{T_n(Q_V)} = \sum_{\overline{W}_n \in \mathcal{W}_n(Q_V)} \lambda(\overline{W}_n) \overline{W}_n, \tag{114}$$

where $\lambda(\overline{W}_n)$ is a positive constant and $\mathcal{W}_n(Q_V)$ is the family of conditional types from $\mathcal{V}^n$ to $\mathcal{Z}^n$, which is the V-shell of a sequence of type Q_V. The joint convexity of the conditional relative entropy yields that

$$\begin{aligned} &I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}] \\ \le& \sum_{\overline{W}_n \in \mathcal{W}_n(Q_V)} \lambda(\overline{W}_n) I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \Phi_{a,n}]. \end{aligned} \tag{115}$$

We can also show that for any element $\overline{W}_n \in \mathcal{W}_n(Q_V)$ we have

$$\begin{aligned} &e^{\phi(\rho, \overline{W}^n_{\mathcal{Z}}, P_{V^n|U^n}, P_{U^n})} \\ =& \sum_u P_{U^n}(u) \sum_z (\sum_v P_{V^n|U^n}(v|u)(\sum_{\overline{W}'_n \in \mathcal{W}_n(Q_V)} \lambda(\overline{W}'_n) \overline{W}'_n(z|v))^{\frac{1}{1-\rho}})^{1-\rho} \\ \ge& \sum_u P_{U^n}(u) \sum_z (\sum_v P_{V^n|U^n}(v|u)(\lambda(\overline{W}_n) \overline{W}_n(z|v))^{\frac{1}{1-\rho}})^{1-\rho} \\ =&\lambda(\overline{W}_n) e^{\phi(\rho, \overline{W}_n, P_{V^n|U^n}, P_{U^n})}. \end{aligned} \tag{116}$$

Due to (44) and the convexity of $x \mapsto e^x$, we have

$$\begin{aligned} &\exp(\rho \mathbf{E}_{\tilde{\Phi}_{a,n}} I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}]) \\ \le&\mathbf{E}_{\tilde{\Phi}_{a,n}} \exp(\rho I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}]) \\ \le&1 + \varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n}), \end{aligned} \tag{117}$$

where $\varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n}) := \exp(n\rho(R_c - R_0 - \sum_{i\in\mathcal{I}^c}(R_i - \delta)) + \phi(\rho, \overline{W}_n, P_{V^n|U^n}, P_{U^n}))$. Note that $\overline{W}_n$ is arbitrary and is not necessarily memoryless. Taking the logarithm, we have

$$\begin{aligned} &\mathbf{E}_{\tilde{\Phi}_{a,n}} I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}] \\ \le&\frac{1}{\rho} \log(1 + \varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n})), \end{aligned} \tag{118}$$

Observe that what we have shown is that the averages over $\tilde{\Phi}_{a,n}$ of $\exp(\rho I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}])$ and $I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}]$ are smaller than Eqs. (117) and (118).

Let $p_1(n)$ be a polynomial function of n. We can see that with probability of $1 - 1/p_1(n)$ the pair $\tilde{\Phi}_{a,n}$ makes $\exp(\rho I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}])$ and $I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}]$ smaller than $p_1(n)$ times Eqs. (117) and (118), respectively. Since the inequalities (104) and (105) hold at least with probability $1 - \frac{3}{16} = \frac{13}{16}$ with random selection of $\Phi_{a,n}$ [17, Eq. (24)], one can take $p_1(n) > \frac{16}{13} 2^{T+1} |\mathcal{W}_n(Q_V)|$ [3], and by doing so we can see that there exists at least a code $\tilde{\Phi}_{a,n}$ such that all elements $\overline{W}_n \in \mathcal{W}_n(Q_V)$ satisfies the inequalities (104) and (105) and

$$\begin{aligned} &I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}] \\ \le&\frac{p_1(n)}{\rho} \log(1 + \varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n})) \le \frac{p_1(n)}{\rho} \varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n}) \end{aligned} \tag{119}$$

$$\begin{aligned} &\exp(\rho I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}]) \\ \le&p_1(n)(1 + \varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n})). \end{aligned} \tag{120}$$

Thus, defining $p_2(n) := p_1(n)(n+1)^{|\mathcal{U}|^2|\mathcal{V}|}|\mathcal{W}_n(Q_V)|$, we obtain

$$\begin{align}
& I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}] \nonumber\\
\le & \sum_{\overline{W}_n \in \mathcal{W}_n(Q_V)} \lambda(\overline{W}_n) I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}] \tag{121}\\
\le & \sum_{\overline{W}_n \in \mathcal{W}_n(Q_V)} \lambda(\overline{W}_n) \frac{p_1(n)}{\rho} \varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n}) \tag{122}\\
\le & \sum_{\overline{W}_n \in \mathcal{W}_n(Q_V)} \frac{p_1(n)(n+1)^{|\mathcal{U}|^2|\mathcal{V}|}}{\rho} \varepsilon_{n,\rho}(\overline{W}^n_{\mathcal{Z}}, Q^n_{V,U}) \tag{123}\\
= & \frac{p_1(n)|\mathcal{W}_n(Q_V)|(n+1)^{|\mathcal{U}|^2|\mathcal{V}|}}{\rho} \varepsilon_{n,\rho}(\overline{W}^n_{\mathcal{Z}}, Q^n_{V,U}) \nonumber\\
= & \frac{p_2(n)}{\rho} \varepsilon_{1,\rho}(\overline{W}_{\mathcal{Z}}, Q_{V,U})^n, \tag{124}
\end{align}$$

where (121), (122), and (123) follow from (115), (119), and (113) and (116), respectively.

Since $\log \varepsilon_{1,\rho}(\overline{W}_{\mathcal{Z}}, Q_{V,U}) = R_c - R_0 - \sum_{i \in \mathcal{I}^c}(R_i - \delta) + \phi(\rho, \overline{W}_{\mathcal{Z}}, Q_{V|U}, Q_U)$, for an arbitrary $\delta > 0$, we can choose a large integer N_1 such that

$$\begin{aligned}
& \inf_{1/n \le \rho \le 1} \log(\frac{p_2(n)}{\rho} \varepsilon_{1,\rho}(\overline{W}_{\mathcal{Z}}, Q_{V,U})^n) \\
\le & \inf_{1/n \le \rho \le 1} \log(\varepsilon_{1,\rho}(\overline{W}_{\mathcal{Z}}, Q_{V,U})^n) + \log p_2(n) + \log n \\
\le & -n(E^{\mathcal{I}}_+(R_p, R_c, (R_i)^T_{i=0}, W) - T\delta)
\end{aligned}$$

for $n \ge N_1$. Since (124) holds with any $\rho \in [1/n, 1]$, we obtain

$$\begin{align}
& \log I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}] \nonumber\\
\le & -n(E^{\mathcal{I}}_+(R_p, R_c, (R_i)^T_{i=0}, W) - T\delta) \tag{125}
\end{align}$$

for $n \ge N_1$.

Since $x \mapsto \exp(x)$ is convex, (115), (116), (113) and (120) yield that

$$\begin{align}
& \exp(\rho I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}]) \nonumber\\
\le & \sum_{\overline{W}_n \in \mathcal{W}_n(Q_V)} \lambda(\overline{W}_n) \exp(\rho I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}]) \nonumber\\
\le & \sum_{\overline{W}_n \in \mathcal{W}_n(Q_V)} \lambda(\overline{W}_n) p_1(n)(1 + \varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n})) \nonumber\\
\le & \sum_{\overline{W}_n \in \mathcal{W}_n(Q_V)} p_1(n)(1 + \varepsilon_{n,\rho}(\overline{W}^n_{\mathcal{Z}}, P_{V^n,U^n})) \nonumber\\
\le & p_1(n)|\mathcal{W}_n(Q_V)|(1 + \varepsilon_{n,\rho}(\overline{W}^n_{\mathcal{Z}}, P_{V^n,U^n})) \nonumber\\
\le & p_2(n)(1 + \varepsilon_{n,\rho}(\overline{W}^n_{\mathcal{Z}}, Q^n_{V,U})) \tag{126}
\end{align}$$

Taking the logarithm, we have

$$\begin{align}
& I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}] \nonumber\\
\le & \frac{\log p_2(n)^2(1 + \varepsilon_{n,\rho}(\overline{W}^n_{\mathcal{Z}}, Q^n_{V,U}))}{\rho} \nonumber\\
\le & \frac{\log(2p_2(n)^2)}{\rho} + n\frac{[\log \varepsilon_{1,\rho}(\overline{W}_{\mathcal{Z}}, Q_{V,U}))]_+}{\rho}. \tag{127}
\end{align}$$

Since $\lim_{\rho \to 0} \frac{[\log \varepsilon_{1,\rho}(\overline{W}_{\mathcal{Z}}, Q_{V,U}))]_+}{\rho} = E^{\mathcal{I}}_-(R_p, R_c, (R_i)^T_{i=0}, W)$, we can choose an integer N_2 such that

$$\begin{align}
& I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}] \nonumber\\
\le & \text{RHS of(127) with } \rho = 1/\sqrt{n} \nonumber\\
\le & n(E^{\mathcal{I}}_-(R_p, R_c, (R_i)^T_{i=0}, W) + T\delta) \tag{128}
\end{align}$$

for $n \ge N_2$.

Therefore, using (125), (128), we can see that (E^b, E^e, $E^{\mathcal{I}}_+$) $E^{\mathcal{I}}_-$) is a universally attainable quadruple of exponents in the sense of Definition 24. ∎

X. Source-channel universal coding for BCC

We prove Theorem 6. In the following, we treat the same ensemble of codes $\Phi_n := (\tilde{\Phi}_{a,n}, \Phi_{b,n}, \Phi_{e,n})$ as that in the proof of Theorem 25 when $T = 2$, $S_1 = S$, $S_0 = E$ and S_2 is the random number subject to the uniform distribution.

We prepare formulas similar to (113):

$$\begin{align}
& \exp(\phi(\rho, \overline{W}^n_{\mathcal{Z}} \circ P_{V^n|U^n}, P_{U^n})) \nonumber\\
\le & (n+1)^{|\mathcal{U}|^2|\mathcal{V}|} \exp(\phi(\rho, \overline{W}^n_{\mathcal{Z}} \circ Q^n_{V|U}, Q^n_U)), \tag{129}\\
& \exp(\phi(\rho, \overline{W}^n_{\mathcal{Y}}, P_{V^n|U^n}, P_{U^n})) \nonumber\\
\le & (n+1)^{|\mathcal{U}|^2|\mathcal{V}|} \exp(\phi(\rho, \overline{W}^n_{\mathcal{Y}}, Q^n_{V|U}, Q^n_U)), \tag{130}\\
& \exp(\phi(\rho, \overline{W}^n_{\mathcal{Y}}, P_{U^n,V^n})) \nonumber\\
\le & (n+1)^{|\mathcal{U}|^2|\mathcal{V}|} \exp(\phi(\rho, \overline{W}^n_{\mathcal{Z}}, Q^n_{U,V})). \tag{131}
\end{align}$$

Since we employ a similar construction, it is sufficient to treat the channel whose input system is the subset $T_n(Q_V)$ of $\mathcal{V}^n$. Similar to (114), we have the following convex combination:

$$\overline{W}^n_{\mathcal{Y}}|_{T_n(Q_V)} = \sum_{\overline{W}_{n,Y} \in \mathcal{W}_{n,Y}(Q_V)} \lambda(\overline{W}_{n,Y}) \overline{W}_{n,Y}, \tag{132}$$

where $\lambda(\overline{W}_{n,Y})$ is a positive constant and $\mathcal{W}_{n,Y}(Q_V)$ is the family of conditional types from $\mathcal{V}^n$ to $\mathcal{Y}^n$, which is the V-shell of a sequence of type Q_V. Similar to (116), we can also show that for any element $\overline{W}_n \in \mathcal{W}_n(Q_V)$ we have

$$\begin{align}
e^{\phi(-\rho, \overline{W}^n_{\mathcal{Y}}, P_{V^n|U^n}, P_{U^n})} \ge \lambda(\overline{W}_{n,Y}) e^{\phi(-\rho, \overline{W}_{n,Y}, P_{V^n|U^n}, P_{U^n})}, \tag{133}\\
e^{\phi(-\rho, \overline{W}^n_{\mathcal{Y}}, P_{U^n,V^n})} \ge \lambda(\overline{W}_{n,Y}) e^{\phi(-\rho, \overline{W}_{n,Y}, P_{U^n,V^n})}, \tag{134}\\
e^{\phi(-\rho, \overline{W}^n_{\mathcal{Z}}, \circ P_{V^n|U^n}, P_{U^n})} \ge \lambda(\overline{W}_n) e^{\phi(-\rho, \overline{W}_n, \circ P_{V^n|U^n}, P_{U^n})}. \tag{135}
\end{align}$$

Due to (45) and (46), any $\overline{W}_n \in \mathcal{W}_n(Q_V)$ and any $\overline{W}_{n,Y} \in \mathcal{W}_{n,Y}(Q_V)$ satisfy

$$\begin{align}
\mathbf{E}_{\Phi_n} P_b[\overline{W}_{n,Y}, \Phi_n] \le & e^{n\rho R_p + \phi(-\rho, \overline{W}_{n,Y}, P_{V^n|U^n}, P_{U^n})} \nonumber\\
& + e^{n\rho(R_p+R_0) + \phi(-\rho, \overline{W}_{n,Y}, P_{U^n,V^n})}, \tag{136}\\
\mathbf{E}_{\Phi_n} P_e[\overline{W}_n, \Phi_n] \le & e^{n\rho R_0 + \phi(-\rho, \overline{W}_n \circ P_{V^n|U^n}, P_{U^n})}. \tag{137}
\end{align}$$

Using (44), we obtain

$$\begin{align}
& \mathbf{E}_{\tilde{\Phi}_{a,n}} \sum_e P_{E_n}(e) \sum_s P_{S_n|E_n}(s|e) \nonumber\\
& \cdot \exp(\rho D(P_{Z^n|S_n=s, E_n=e, \tilde{\Phi}_{a,n}} \| P_{Z^n|E_n=e, \tilde{\Phi}_{a,n}})) \nonumber\\
\le & 1 + \varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n}). \tag{138}
\end{align}$$

Let $p_3(n) := 3|\mathcal{W}_n(Q_V)| + |\mathcal{W}_{n,Y}(Q_V)|$ and $p_4(n) := 2p_3(n)$. Then, from (136), (137), (138), and (118), all of the following conditions hold at least with probability of $1-p_3(n)/p_4(n) = \frac{1}{2}$:

$$\begin{aligned}
& P_b[\overline{W}_{n,Y}, \Phi_n] \\
\le & p_4(n)\Big(e^{n\rho R_p+\phi(-\rho,\overline{W}_{n,Y},P_{V^n|U^n},P_{U^n})} + e^{n\rho(R_p+R_0)+\phi(-\rho,\overline{W}_{n,Y},P_{U^n,V^n})}\Big), \\
& P_e[\overline{W}_n, \Phi_n] \\
\le & p_4(n)e^{n\rho R_0+\phi(-\rho,\overline{W}_n\circ P_{V^n|U^n},P_{U^n})}, \\
& \sum_e P_{E_n}(e) \sum_s P_{S_n|E_n}(s|e) \exp(\rho D(P_{Z^n|S_n=s,E_n=e,\tilde{\Phi}_{a,n}}\|P_{Z^n|E_n=e,\tilde{\Phi}_{a,n}})) \\
\le & p_4(n)(1+\varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n})), \\
& I(S_{\mathcal{I},n} : Z^n|S_{0,n})[\overline{W}_n, \tilde{\Phi}_{a,n}]) \\
\le & \frac{p_4(n)}{\rho} \log(1+\varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n}))
\end{aligned}$$

for any $\overline{W}_n \in \mathcal{W}_n(Q_V)$ and any $\overline{W}_{n,Y} \in \mathcal{W}_{n,Y}(Q_V)$.

So, we choose $\Phi_{a,n}$ satisfying the all of the above conditions. Next, we consider the random variable E_n subject to the uniform distribution on $\mathcal{E}_n$. Then, when e is regarded as a random variable, the random variable e satisfies all of the following conditions at least with probability of $1 - p_3(n)/p_4(n) = \frac{1}{2}$:

$$\begin{aligned}
& P_b(E_n = e)[\overline{W}_{n,Y}, \Phi_n] \\
\le & p_4(n)^2(e^{n\rho R_p+\phi(-\rho,\overline{W}_{n,Y},P_{V^n|U^n},P_{U^n})} + e^{n\rho(R_p+R_0)+\phi(-\rho,\overline{W}_{n,Y},P_{U^n,V^n})}), \\
& P_e(E_n = e)[\overline{W}_n, \Phi_n] \\
\le & p_4(n)^2 e^{n\rho R_0+\phi(-\rho,\overline{W}_n\circ P_{V^n|U^n},P_{U^n})}, \\
& \sum_s P_{S_n|E_n}(s|e) \exp(\rho D(P_{Z^n|S_n=s,E_n=e,\tilde{\Phi}_{a,n}}\|P_{Z^n|E_n=e,\tilde{\Phi}_{a,n}})) \\
\le & p_4(n)^2(1+\varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n})), \\
& \sum_s P_{S_n|E_n}(s|e) D(P_{Z^n|S_n=s,E_n=e,\tilde{\Phi}_{a,n}}\|P_{Z^n|E_n=e,\tilde{\Phi}_{a,n}}) \\
= & I(S_n : Z^n|E_n = e)[\overline{W}_n, \tilde{\Phi}_{a,n}] \\
\le & \frac{p_4(n)^2}{\rho} \log(1+\varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n})). \qquad (139)
\end{aligned}$$

Thus, there exist $|\mathcal{E}_n|/2$ elements $e \in \mathcal{E}_n$ satisfies the above conditions: So, we denote the set of such elements in $\mathcal{E}'_n$. We choose $\tilde{p}_3(n) := 2|\mathcal{W}_n(Q_V)| + |\mathcal{W}_{n,Y}(Q_V)|$. Then, the random variable s satisfies all of the following conditions at least with probability of $1 - \tilde{p}_3(n)/p_4(n) \ge \frac{1}{2}$:

$$\begin{aligned}
& P_b(S_n = s, E_n = e)[\overline{W}_{n,Y}, \Phi_n] \\
\le & p_4(n)^3(e^{n\rho R_p+\phi(-\rho,\overline{W}_{n,Y},P_{V^n|U^n},P_{U^n})} + e^{n\rho(R_p+R_0)+\phi(-\rho,\overline{W}_{n,Y},P_{U^n,V^n})}), \\
& \exp(\rho D(P_{Z^n|S_n=s,E_n=e,\tilde{\Phi}_{a,n}}\|P_{Z^n|E_n=e,\tilde{\Phi}_{a,n}})) \\
\le & p_4(n)^3(1+\varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n}), \\
& D(P_{Z^n|S_n=s,E_n=e,\tilde{\Phi}_{a,n}}\|P_{Z^n|E_n=e,\tilde{\Phi}_{a,n}}) \\
\le & \frac{p_4(n)^3}{\rho} \log(1+\varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n}))
\end{aligned}$$

Thus, there exist $|\mathcal{S}_n|/2$ elements $s \in \mathcal{S}_n$ satisfies the above conditions. So, we denote the set of such elements in $\mathcal{S}'_n$.

Now, we assume that S_n and E_n satisfies an arbitrary distribution on $\mathcal{S}'_n \times \mathcal{E}'_n$. Then,

$$\begin{aligned}
& P_e[\overline{W}_n, \Phi_n] \le p_4(n)^2 e^{n\rho R_0+\phi(-\rho,\overline{W}_n\circ P_{V^n|U^n},P_{U^n})}, && (140) \\
& P_b[\overline{W}_{n,Y}, \Phi_n] \\
\le & p_4(n)^3\Big(e^{n\rho R_p+\phi(-\rho,\overline{W}_{n,Y},P_{V^n|U^n},P_{U^n})} \\
& + e^{n\rho(R_p+R_0)+\phi(-\rho,\overline{W}_{n,Y},P_{U^n,V^n})}\Big), && (141) \\
& I(S_n : Z^n|E_n)[\overline{W}_n, \tilde{\Phi}_{a,n}] \\
\le & \sum_e P_{E_n}(e) \sum_s P_{S_n}(s|e) D(P_{Z^n|S_n=s,E_n=e,\tilde{\Phi}_{a,n}}\|P_{Z^n|E_n=e,\tilde{\Phi}_{a,n}}) \\
\le & \frac{p_4(n)^3}{\rho} \log(1+\varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n})), && (142) \\
& e^{\rho I(S_n:Z^n|E_n)[\overline{W}_n,\tilde{\Phi}_{a,n}]} \\
\le & \sum_e P_{E_n}(e) \sum_s P_{S_n}(s|e) e^{\rho D(P_{Z^n|S_n=s,E_n=e,\tilde{\Phi}_{a,n}}\|P_{Z^n|E_n=e,\tilde{\Phi}_{a,n}})} \\
\le & p_4(n)^3(1+\varepsilon_{n,\rho}(\overline{W}_n, P_{V^n,U^n}). && (143)
\end{aligned}$$

Similar to (124) and (126), defining $p_5(n) := p_4(n)^3(n+1)^{|\mathcal{U}|^2|\mathcal{V}|}|\mathcal{W}_n(Q_V)|$, we obtain

$$I(S_n : Z^n|E_n)[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}] \le \frac{p_5(n)}{\rho} \varepsilon_{1,\rho}(\overline{W}_{\mathcal{Z}}, Q_{V,U})^n \qquad (144)$$

$$\exp(\rho I(S_n : Z^n|E_n)[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}]) \le p_5(n)(1+\varepsilon_{n,\rho}(\overline{W}^n_{\mathcal{Z}}, Q^n_{V,U})). \qquad (145)$$

Further, defining $p_6(n) := p_4(n)^2(n+1)^{|\mathcal{U}|^2|\mathcal{V}|}|\mathcal{W}_n(Q_V)|$, we obtain

$$\begin{aligned}
& P_e[\overline{W}^n_{\mathcal{Z}}, \Phi_n] \\
= & \sum_{\overline{W}_n\in\mathcal{W}_n(Q_V)} \lambda(\overline{W}_n) P_e[\overline{W}_n, \Phi_n] && (146) \\
\le & \sum_{\overline{W}_n\in\mathcal{W}_n(Q_V)} \lambda(\overline{W}_n) p_4(n)^2 e^{n\rho R_0+\phi(-\rho,\overline{W}_n\circ P_{V^n|U^n},P_{U^n}))} && (147) \\
\le & \sum_{\overline{W}_n\in\mathcal{W}_n(Q_V)} p_4(n)^2(n+1)^{|\mathcal{U}|^2|\mathcal{V}|} e^{n\rho R_0+\phi(-\rho,\overline{W}^n_{\mathcal{Z}}\circ Q^n_{V|U},Q^n_U))} && (148) \\
= & p_4(n)^2|\mathcal{W}_n(Q_V)|(n+1)^{|\mathcal{U}|^2|\mathcal{V}|} e^{n\rho R_0+\phi(-\rho,\overline{W}^n_{\mathcal{Z}}\circ Q^n_{V|U},Q^n_U))} \\
= & p_6(n) e^{n(\rho R_0+\phi(-\rho,\overline{W}_{\mathcal{Z}}\circ Q_{V|U},Q_U))}, && (149)
\end{aligned}$$

where (146), (147), and (148) follow from (114), (140), and (129) and (135).

Similarly, using (141), (132), (130), (131), (133), and (134), we obtain

$$\begin{aligned}
& P_b[\overline{W}^n_{\mathcal{Y}}, \Phi_n] \\
\le & p_4(n)^3|\mathcal{W}_{n,Y}(Q_V)|(n+1)^{|\mathcal{U}|^2|\mathcal{V}|} \\
& \cdot (e^{n\rho R_p+\phi(-\rho,\overline{W}^n_{\mathcal{Y}},Q^n_{V|U},Q^n_U)} + e^{n\rho(R_p+R_0)+\phi(-\rho,\overline{W}^n_{\mathcal{Y}},Q^n_{U,V})}) \\
= & p_5(n)(e^{n(\rho R_p+\phi(-\rho,\overline{W}_{\mathcal{Y}},Q_{V|U},Q_U))} + e^{n(\rho(R_p+R_0)+\phi(-\rho,\overline{W}_{\mathcal{Y}},Q_{U,V}))}). \\
& && (150)
\end{aligned}$$

Therefore, from (149) and (150), for an arbitrary $\delta > 0$, we can choose an integer N_0 such that

$$\log P_e[\overline{W}^n_{\mathcal{Z}}, \Phi_n] \le -n(E^e(R_p, R_c, R_0, R_1, W) - \delta), \qquad (151)$$

$$\log P_b[\overline{W}^n_{\mathcal{Y}}, \Phi_n] \le -n(E^b(R_p, R_c, R_0, R_1, W) - \delta). \qquad (152)$$

Similar to (125), using (142), for an arbitrary $\delta > 0$, we can choose an integer N_1 such that

$$\begin{aligned}&\log I(S_n : Z^n|E_n)[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}]\\ \le& -n(E_+(R_p, R_c, R_0, R_1, W) - \delta) \qquad (153)\end{aligned}$$

for $n \ge N_1$.

Similar to (128), using (143), for an arbitrary $\delta > 0$, we can choose an integer N_2 such that

$$\begin{aligned}&I(S_n : Z^n|E_n)[\overline{W}^n_{\mathcal{Z}}, \tilde{\Phi}_{a,n}]\\ \le& n(E_-(R_p, R_c, R_0, R_1, W) + \delta) \qquad (154)\end{aligned}$$

for $n \ge N_2$.

Therefore, using (151), (152), (153), and (154), we can see that (E^b, E^e, E_+, E_-) is a universally attainable quadruple of exponents in the sense of Definition 5. ■

XI. Conclusion

In order to treat secure multiplex coding with dependent and non-uniform multiple messages and a common message, we have generalized resolvability to the case when input random variable is subject to a non-uniform distribution. Two kinds of generalization have been given. The first one (Theorem 10) is a simple extension of Han-Verdú's channel resolvability coding [8] with the non-uniform inputs. The second one (Theorem 12) uses randomly chosen affine mapping satisfying Condition 11 with the non-uniform inputs.

We have constructed two kinds of codes for the above type of SMC. Similar to BCC in [5], the first construction has two steps. In the first step, similar to the BCD encoder, we apply superposition random coding. In the second step, as is illustrated in Fig. 1, we split the confidential message into the private message B_2 and a part B_1 of the common message encoded by the BCD encoder. Employing the second type of channel resolvability, we have derived a non-asymptotic formula for the average leaked information under this kind of code construction. On the other hand, in the second construction, the confidential message is simply sent as the private message encoded by the BCD encoder. Hence, it has only one step. Employing the first type of channel resolvability, we have derived a non-asymptotic formula for the average leaked information under this kind of code construction.

Extending the above formula for the first construction to the asymptotic case, we have derived the capacity region for SMC defined in our general setting, in which, the message is allowed to be dependent and non-uniform while it has to satisfy the asymptotic uniformity. Using the both formulas, We have also derived the exponential decreasing rate of leaked information. While the first formula gives an upper bound in any case, the second one gives a better upper bound in some specific cases.

We have also given a practical construction for SMC by using an ordinary linear code.

Further, we have given a universal code for SMC, which does not depend on the channel. Extending this result, we have derived a source-channel universal code for BCC, which does not depend on the channel or the source distribution.

Appendix

Lemma 26: Let A_n be a sequence of random variables on the set $\mathcal{A}_n$ with the cardinality e^{nR} and B_n be a sequence of other random variables.

$$\lim_{n\to\infty} \frac{1}{n} H(A_n|B_n) = R \qquad (155)$$

if and only if

$$\lim_{n\to\infty} \frac{1}{n} H_{1+a/n}(A_n|B_n) = R \qquad (156)$$

for any $a > 0$.

Proof: For an arbitrary small number $\epsilon > 0$, we define a probability

$$\delta_n := P_{A^n,B^n}\{(a,b)| - \frac{1}{n}\log P_{A^n|B^n}(a|b) \le R - \epsilon\}.$$

(158) of Lemma 27 guarantees that

$$H(A_n|B_n) \le nR - \delta_n(e^{-n\epsilon} - 1 + n\epsilon).$$

That is,

$$\delta_n \le \frac{R - \frac{1}{n}H(A_n|B_n)}{\frac{e^{-n\epsilon}-1}{n} + \epsilon}.$$

Thus, $\lim_{n\to\infty} \delta_n = 0$. (159) of Lemma 27 guarantees that

$$H_{1+a/n}(A_n|B_n) \ge -\frac{n}{a}\log((1-\delta_n)e^{a(\epsilon-R)} + \delta_n)$$

Thus,

$$\begin{aligned}\liminf_{n\to\infty} \frac{1}{n} H_{1+a/n}(A_n|B_n) \ge& \liminf_{n\to\infty} -\frac{1}{a}\log((1-\delta_n)e^{a(\epsilon-R)} + \delta_n)\\ =& R - \epsilon.\end{aligned}$$

Since $\epsilon > 0$ is arbitrary,

$$\liminf_{n\to\infty} \frac{1}{n} H_{1+a/n}(A_n|B_n) \ge R,$$

which implies

$$\lim_{n\to\infty} \frac{1}{n} H_{1+a/n}(A_n|B_n) = R.$$

Combining relation (23), we obtain the desired argument. ■

Lemma 27: Let A be a random variable on the set $\mathcal{A}$ with the cardinality M and B be another random variable. For any $\epsilon_1 > 0$ and $\epsilon_2 > 0$, we define the subset of joint distribution for A and B

$$\mathcal{P}_{\epsilon_1,\epsilon_2,M} := \{P_{A,B}|P_{A,B}\{(a,b)| - \log P_{A|B}(a|b) \le \log M - \epsilon_1\} \le \epsilon_2\}. \qquad (157)$$

Then,

$$\max_{P_{A,B}\in\mathcal{P}_{\epsilon_1,\epsilon_2,M}} H(A|B)[P_{A,B}] \le \log M - \epsilon_2(e^{-\epsilon_1} - 1 + \epsilon_1) \qquad (158)$$

$$\min_{P_{A,B}\in\mathcal{P}_{\epsilon_1,\epsilon_2,M}} H_{1+\rho}(A|B)[P_{A,B}] \ge -\frac{1}{\rho}\log((1-\epsilon_2)\frac{e^{\rho\epsilon_1}}{M^\rho} + \epsilon_2). \qquad (159)$$

Here, since the region $\mathcal{P}_{\epsilon_1,\epsilon_2,M}$ is compact, the above maximum and minimum exist.

Proof: For any integer k, we define the set

$$\begin{aligned}\mathcal{P}_{\epsilon_1,\epsilon_2,M,k} &:= \left\{ P_A \;\middle|\; \begin{array}{l} P_A\{a| -\log P_A(a) \le \log M - \epsilon_1\} \le \epsilon_2, \\ |\{a| -\log P_A(a) \le \log M - \epsilon_1\}| = k \end{array} \right\} \\ \hat{\mathcal{P}}_{\epsilon_1,\epsilon_2,M} &:= \{P_A | P_A\{a| -\log P_A(a) \le \log M - \epsilon_1\} \le \epsilon_2\}.\end{aligned}$$

The possible range of integer k is the integers in $[1, \epsilon_2 M e^{-\epsilon_1}]$. Then,

$$\begin{aligned}&\max_{P_A \in \mathcal{P}_{\epsilon_1,\epsilon_2,M,k}} H(A)[P_A] \\ =& f(k) := \epsilon_2(\log k - \log \epsilon_2)(1-\epsilon_2)(\log(M-k) - \log(1-\epsilon_2)).\end{aligned}$$

Taking the derivative, we have

$$f'(x) = \frac{\epsilon_2}{x} - \frac{1-\epsilon_2}{M-x},$$

which is positive when $x < M\epsilon_2$. Hence,

$$\begin{aligned}&\max_{P_A \in \hat{\mathcal{P}}_{\epsilon_1,\epsilon_2,M}} H(A)[P_A] \\ =& f(\epsilon_2 M e^{-\epsilon_1}) \\ =& \epsilon_2(\log M - \epsilon_1) + (1-\epsilon_2)(\log M + \log(1-\epsilon_2 e^{-\epsilon_1}) - \log(1-\epsilon_2)) \\ =& \log M - \epsilon_2\epsilon_1 + (1-\epsilon_1)\log(1 + \frac{\epsilon_2(1-e^{-\epsilon_1})}{1-\epsilon_2}) \\ \le& \log M - \epsilon_2\epsilon_1 + (1-\epsilon_1)\frac{\epsilon_2(1-e^{-\epsilon_1})}{1-\epsilon_2} \\ =& \log M - \epsilon_2(e^{-\epsilon_1} - 1 + \epsilon_1).\end{aligned}$$

Since $\log M - \epsilon_2(e^{-\epsilon_1} - 1 + \epsilon_1)$ is linear concerning ϵ_2, we obtain (158).

$$\max_{P_A \in \hat{\mathcal{P}}_{\epsilon_1,\epsilon_2,M}} e^{-\rho H_{1+\rho}(A)[P_A]} \le (1-\epsilon_2)\frac{e^{\rho\epsilon_1}}{M^\rho} + \epsilon_2^{1+\rho} \le (1-\epsilon_2)\frac{e^{\rho\epsilon_1}}{M^\rho} + \epsilon_2.$$

Since $(1-\epsilon_2)\frac{e^{\rho\epsilon_1}}{M^\rho} + \epsilon_2$ is linear concerning ϵ_2, we obtain

$$\max_{P_{A|B} \in \mathcal{P}_{\epsilon_1,\epsilon_2,M}} e^{-\rho H_{1+\rho}(A|B)[P_{A|B}]} \le (1-\epsilon_2)\frac{e^{\rho\epsilon_1}}{M^\rho} + \epsilon_2,$$

which implies (159). ■

ACKNOWLEDGMENT

RM would like to thank Prof. H. Yamamoto to teach him the secure multiplex coding. A part of this research was done during his stay at the Institute of Network Coding, the Chinese University of Hong Kong, and Department of Mathematical Sciences, Aalborg University. He greatly appreciates the hospitality by Prof. R. Yeung and Prof. O. Geil.

This research was partially supported by the MEXT Grant-in-Aid for Young Scientists (A) No. 20686026 and (B) No. 22760267, and Grant-in-Aid for Scientific Research (A) No. 23246071. The Center for Quantum Technologies is funded by the Singapore Ministry of Education and the National Research Foundation as part of the Research Centres of Excellence programme.

REFERENCES

[1] S. Arimoto, “On the converse to the coding theorem for discrete memoryless channels,” *IEEE Trans. Inform. Theory*, vol. 19, no. 3, pp. 357–359, May 1973.

[2] M. R. Bloch, “Achieving secrecy: Capacity vs. resolvability,” in *Proc. ISIT 2011*, Saint-Petersburg, Russia, Aug. 2011, pp. 633–637.

[3] I. Csiszár and J. Körner, *Information Theory: Coding Theorems for Discrete Memoryless Systems*. Budapest, Hungary: Akadémiai Kiadó, 1981.

[4] I. Csiszár, “Almost independence and secrecy capacity,” *Problems of Information Transmission*, vol. 32, no. 1, pp. 40–47, 1996.

[5] I. Csiszár and J. Körner, “Broadcast channels with confidential messages,” *IEEE Trans. Inform. Theory*, vol. 24, no. 3, pp. 339–348, May 1978.

[6] P. Delsarte and P. M. Piret, “Algebraic constructions of shannon codes for regular channels,” *IEEE Trans. Inform. Theory*, vol. 28, no. 4, pp. 593–599, Jul. 1982.

[7] R. G. Gallager, *Information Theory and Reliable Communication*. New York: John Wiley & Sons, 1968.

[8] T. S. Han and S. Verdú, “Approximation theory of output statistics,” *IEEE Trans. Inform. Theory*, vol. 39, no. 3, pp. 752–772, May 1993.

[9] T. S. Han, “Folklore in source coding: Information-spectrum approach,” *IEEE Trans. Inform. Theory*, vol. 51, no. 2, pp. 747–753, Feb. 2005.

[10] M. Hayashi, “General non-asymptotic and asymptotic formulas in channel resolvability and identification capacity and its application to wire-tap channel,” *IEEE Trans. Inform. Theory*, vol. 52, no. 4, pp. 1562–1575, Apr. 2006.

[11] ——, “Exponential decreasing rate of leaked information in universal random privacy amplification,” *IEEE Trans. Inform. Theory*, vol. 57, no. 6, pp. 3989–4001, Jun. 2011.

[12] M. Hayashi and R. Matsumoto, “Construction of wiretap codes from ordinary channel codes,” in *Proc. 2010 IEEE ISIT*, Austin, Texas, USA, Jun. 2010, pp. 2538–2542.

[13] ——, “Universally attainable error and information exponents, and equivocation rate for the broadcast channels with confidential messages,” in *Proc. 49th Annual Allerton Conf.*, Allerton House, Monticello, IL, USA, 2011, pp. 439–444, arXiv:1104.4285.

[14] Y. Kaspi and N. Merhav, “Error exponents for broadcast channels with degraded message sets,” *IEEE Trans. Inform. Theory*, vol. 57, no. 1, pp. 101–123, Jan. 2011.

[15] D. Kobayashi, H. Yamamoto, and T. Ogawa, “How to attain the ordinary channel capacity securely in wiretap channels,” in *Proc. 2005 IEEE Information Theory Workshop on Theory and Practice in Information-Theoretic Security*, Oct. 2005, pp. 13–18, arXiv:cs/0509047.

[16] J. Körner and K. Marton, “General broadcast channels with degraded message sets,” *IEEE Trans. Inform. Theory*, vol. 23, no. 1, pp. 60–64, Jan. 1977.

[17] J. Körner and A. Sgarro, “Universally attainable error exponents for broadcast channels with degraded message sets,” *IEEE Trans. Inform. Theory*, vol. 26, no. 6, pp. 670–679, Nov. 1980.

[18] Y. Liang, H. V. Poor, and S. Shamai (Shitz), *Information Theoretic Security*. Hanover, MA, USA: NOW Publishers, 2009.

[19] R. Matsumoto and M. Hayashi, “Secure multiplex coding with a common message,” in *Proc. 2011 IEEE ISIT*, Saint-Petersburg, Russia, Jul. 2011, pp. 1931–1935, arXiv:1101.4036.

[20] U. M. Maurer, “The strong secret key rate of discrete random triples,” in *Communications and Cryptography – Two Sides of One Tapestry*, R. E. Blahut *et al.*, Eds. Kluwer Academic Publishers, 1994, pp. 271–285.

[21] A. D. Wyner, “The wire-tap channel,” *Bell System Tech. J.*, vol. 54, no. 8, pp. 1355–1387, Oct. 1975.